



User's Guide Model DV25 Dual Range AC Voltage Detector + Flashlight

Safety

WARNING: Risk of Electrocution. Before use, always test the Voltage Detector on a known live circuit to verify proper operation

WARNING: Risk of Electrocution. Keep hands and fingers on the body of the probe and away from the probe tip

CAUTION: Read, understand and follow Safety Rules and Operating Instructions in this manual before using this product.

Do not attempt to repair this unit. There are no user serviceable parts.

Do not expose the unit to extreme temperatures or high humidity

Do not use the unit if it is wet or damaged

Do not apply more than the rated voltage between the probe tip and ground.

Do not operate with the case open



This symbol, adjacent to another symbol or terminal, indicates the user the user must refer to the manual for further information.



This symbol, adjacent to a terminal, indicates that, under normal use, hazardous voltages may be present



Double insulation

Specifications

Voltage Sensitivity 100V to 1000V AC, 50/60Hz

24V to 1000V AC, 50/60Hz

Detection distance <0.2"

Operating Temperature 32 to 122°F (0 to 50°C)

Storage Temperature -4 to 140°F (-20 to 60°C)

Altitude Operating below 2000 meters

Relative Humidity 80% up to 31°C, decreasing to 50% at 50°C

Battery 2 AAA batteries

Dimensions/Weight 6.25x1" (159x25mm) / 1.5oz (42g)

Safety For indoor use and in accordance with Overvoltage Category IV-1000V, Pollution Degree 2.

Operating Instructions

AC VOLTAGE DETECTION

- For low voltage testing (24 to 100V), press and hold the 24V button (5). For standard electrical work (>100V, this is not necessary).
- Touch the probe tip (7) to the hot conductor or insert into the hot side of the electrical outlet.
- If AC voltage is present, the detector cone will illuminate (6) and the detector will beep.

NOTE: The detector is designed with high sensitivity. Static electricity or other sources of energy may randomly trip the sensor. This is normal operation.

FLASHLIGHT

Press and hold the flashlight ON/OFF button (2) to turn on the flashlight (1).

BATTERY INSTALLATION

- Remove the end cap (3) by gently lifting the pocket clip (4) to release the catch.
- Insert two AAA batteries (observe polarity).
- Replace the end cap

NOTE: If your meter does not work properly, check the battery to make sure that it still good and that it is properly inserted.



You, as the end user, are legally bound (Battery ordinance) to return all used batteries and accumulators; disposal in the household garbage is prohibited!

You can hand over your used batteries / accumulators, gratuitously, at the collection points for our branches in your community or wherever batteries / accumulators are sold!

Disposal: Follow the valid legal stipulations in respect of the disposal of the device at the end of its lifecycle

