

AD-8541-PC



A&D Company, Ltd.

Wireless Communication Interface

INSTRUCTION MANUAL

Note

© 2017 A&D Company, Limited. All rights reserved.

- No part of this publication may be reproduced, transmitted, transcribed, or translated into any language in any form by any means without the written permission of A&D.
- The contents of this manual and the specifications of the instrument covered by this manual are subject to change for improvement without notice.
- The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by A&D is under license.

1WMPD4003796

1. Compliance

1.1. Compliance with FCC Rules

This device contains transmitter module FCC ID : RYYEYSHCN
This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions : (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. (FCC = Federal Communications Commission in the U.S.A.)

FCC warning

Changes or modification not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note :

This equipment has been tested and found to comply with the limits for a class A digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his / her own expense.

1.2. IC

IC RADIATION EXPOSURE STATEMENT FOR CANADA

This device complies with Industry Canada license-exempt RSS standards. Operation is subject to the following two conditions : (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

This device contains transmitter module IC : 4389B-EYSHCN

2. Precautions

Consider the following cautions when the AD-8541-PC is used.

- ⚠ Caution Do not disassemble the device. Doing so may damage the device and cause failure, and the warranty will void.

3. Outline and Features

The AD-8541-PC is a wireless communication interface that connects to a USB port of a computer and can communicate with A&D weighing instruments equipped with Bluetooth. Read this manual before use.


4. Names

Connection switch

Press and hold the switch for several seconds to start bluetooth pairing.

Monitoring LED

When the AD-8541-PC is connected to a USB port of a computer, the current status can be monitored using this LED.



Monitoring LED		Status of the AD-8541-PC
Color	Action	
Green	Lit	Scanning device
Green	Blinking	Communicating with device
Orange	Blinking	Pairing with (scanning) device
Red	Blinking	Error

Packing List

AD-8541-PC 1 Instruction manual (This manual) 1

5. Bluetooth Paring

Perform Bluetooth pairing before using for the first time in order to communicate with the device. Perform Bluetooth pairing again if connection with the device is lost.

- Step 1. Connect the AD-8541-PC to a USB port of a computer.
Press and hold the connection switch for approximately 3 to 4 seconds until the LED changes to blinking orange.
- Step 2. Turn on the weighing instrument to communicate with.
Wait for the LED to blink green. Turn off other Bluetooth devices if present.
- Step 3. When pairing is complete and the connection is established, the LED blinks green.

6. Use

Note

Install the driver software on the computer before using the AD-8541-PC. Installation only needs to be done once. Refer to "10. Installation of Driver Software". Do not connect to USB ports other than those of computer.

Step 1. Connect the AD-8541-PC to a USB port of a computer.

Step 2. Confirm that the monitoring LED is lit in green. If it is not lit in green, refer to "7. Check Before Calling for Service".

Step 3. When a connection has been established, the LED is blinks green.

Step 4. WinCT and other applications can communicate when they are run on the computer. Confirm the COM port number that is displayed for the USB serial port in the device manager. Refer to "8. Specifications" concerning serial communication settings.

7. Check Before Calling for Service

Principal troubleshooting list for communication.

Check	Treatment
Is LED lit in green ?	Turn the device off and on again. Press and hold the connection switch.
Is LED blinking green ?	Turn the device off and on again. Perform pairing again. Refer to "5. Bluetooth Paring".
Is the driver software installed on the computer ?	Install driver software. Refer to "10. Installation of Driver Software".
Are communication settings correct ?	Confirm the settings of the computer application and AD-8541-PC.
Is the correct COM port displayed in the application ?	Insert AD-8541-PC again. Confirm that the correct COM port is the display.
Is the AD-8541-PC inserted into a USB port other than that of the computer?	Insert into a USB port of a computer.

8. Specifications

Communication range	Up to 10 m
Power supply	From USB port
Compatible communication devices	A&D weighing instruments equipped with Bluetooth #1
Operating system	Windows XP/Vista/7/8.1/10 (applicable to 32bit and 64bit) #2
Ambient operating temperature and humidity	-10 to 40 °C, Less than 85 %RH (No condensation)
Dimensions	Approx. 24 mm (W) × 12 mm (H) × 74 mm (D)
Mass	Approx. 15 g
Wireless communication	EYSHCNZXX (TAIYO YUDEN CO. LTD.) Bluetooth 4.2 (Bluetooth Low Energy)
Parameters of serial communication	Baud rate : 2400 bps Bit length / Parity : 7 bit / even Stop bit : 1 bit

#1 Refer to the A&D website concerning applicable instruments equipped with Bluetooth.

#2 Windows is a registered trademark of Microsoft Corporation.

9. Bluetooth Communication

The effective range of Bluetooth communication is 10 m or less in an unobstructed space. If there is an obstacle such as a wall between Bluetooth devices, the range of communication will be shorter. Interference may be caused near the following devices that use the 2.4 GHz frequency band, which is the same as for Bluetooth. Therefore, this device is not suited for uses that require reliability.

- Wireless LAN
- Bluetooth devices (such as mobile phones)
- Home appliances such as microwave ovens

10. Installation of Driver Software

The driver software is automatically installed with Windows 8.1 or later. If the driver cannot be installed, download the software from [Support] - [Software] of the A&D website. Refer to the instruction manual included with downloaded files.