

BESANTEK Pen Digital Multimeter is a pen-style digital multimeter for general electrical maintenance and testing, and includes a brilliant LED at the pen tip for a clear view of the measurement target.

Features:

- Lightweight, compact and easy to use.
- 4000 counts LCD.
- Full automatic measurement, voltage measurement and resistor measurement.
- Continuity check.
- Diode measurement.
- Data hold function.
- Low battery warning indicator.
- Pen light provided.
- Backlight LCD.
- Auto off function.
- Accessories: Instruction manual, fixture, soft pouch and battery.



BST-MT267

Technical Specification:

| BST-MT267 | | | | | | | |
|--------------|----------------------------------|-----------------|------|-------|-------|-----|-----------------|
| DC Voltage | Range | 4V | 40V | 400V | 600V | | |
| | Resolution | 1mV | 10mV | 100mV | 1V | | |
| | Accuracy | ±(1%rdg+3dgt) | | | | | |
| | Input Impedance | 10MΩ | | | | | |
| AC Voltage | Range | 4V | 40V | 400V | 600V | | |
| | Resolution | 1mV | 10mV | 100mV | 1V | | |
| | Accuracy | ±(1.5%rdg+5dgt) | | | | | |
| | Input Impedance | 10MΩ | | | | | |
| Resistance | Range | 400Ω | 4kΩ | 40kΩ | 400kΩ | 4MΩ | 40MΩ |
| | Resolution | 0.1Ω | 1Ω | 10Ω | 100Ω | 1kΩ | 10kΩ |
| | Accuracy | ±(1.5%rdg+3dgt) | | | | | ±(2.5%rdg+4dgt) |
| | OL Protection | 500V DC | | | | | |
| Continuity | Range | 400.0Ω | | | | | |
| | Buzzer | Less than 25Ω | | | | | |
| Diode Test | Test voltage approx. 0.3V to 2V | | | | | | |
| Power Source | DC 3V (CR2032) x 1 | | | | | | |
| Dimensions | 196 (L) x 35.8 (W) x 28.3 (D) mm | | | | | | |
| Weight | Approx. 105g (battery included) | | | | | | |

Ordering Information:

- BST-MT267: Pen Digital Multimeter.



Safety Standard:

- EN 61010-1 CAT III 600V, EN 61326-1