

BESANTEK Voltage/Continuity Tester is an LED type voltage tester which can check AC/DC voltages up to 1000V. It also can test continuity and phase rotation and incorporates a rubberized double-molded housing with a waterproof design (IP65).

Features:

- Voltage test: 12V to 1000V AC/DC (8 LEDs) with indication by buzzer.
- Voltage range: 12V, 24V, 50V, 120V, 230V, 400V, 750V and 1000V.
- Test leads positioned at 19mm apart.
- Interchangeable probe tip for 2mm & 4mm.
- Polarity test: LED +/-.
- Audible continuity test.
- Phase rotation test.
- Self-test button to ensure proper function of the device prior to testing.
- Waterproof design and protection class: IP65.
- Phase/Neutral identification.
- Rubberized double-molded housing.
- ELCB/RCD trip test.
- Flashlight function.
- Accessories: Instruction manual and battery.



BST-MT297

Technical Specification:

BST-MT297	
Voltage Test	12V to 1000V AC/DC
Voltage Range	12V/24V/50V/120V/230V/400V/750V/1000V
Working Frequency	40Hz~65Hz
Voltage Protection	1100V AC/DC
Continuity Range	< 200kΩ
Phase Rotation Test Range	100V~1000V measure between 2 phases, instrument in hand
Operating Temperature	0°C~40°C
Operating Humidity	80%RH max.
Probe Distance	19mm apart
Power Source	1.5V (AAA) x 2
Dimensions	248 (L) x 68 (W) x 34 (D) mm
Weight	Approx. 215g (battery included)

Ordering Information:

- BST-MT297: Voltage/Continuity Tester.



Safety Standard:

- IEC/EN 61010-1 CAT III 1000V, IEC/EN 61010-1 CAT IV 600V, IEC/EN 61243-3, EN 61326-1