

BESANTEK Non-Contact Low Voltage Detector is intended to check for the presence of AC voltage. Signaling the user with an intermittent tone and a flashing LED. They are used to detect voltage in outlets, lighting fixture, wires and cables or to find a break in a wire.

Features:

- Microprocessor controlled smart voltage detector.
- Bright LED and audible alarm sound when voltage is present.
- Designed for non-contact voltage detection.
- Sensitivity adjustable with thumbwheel.
- Adjustable for use on power wiring plus lighting, thermostats and other low voltage circuits.
- LED indication for battery condition.
- Identify hot and neutral.
- Accessories: Instruction manual and battery.

**BST-VT107**

Technical Specification:

BST-VT107	
Voltage Detection	5V ~ 1000V AC
Frequency	50 ~ 500 Hz
Measurement Category	CAT IV 1000V
Indication	LED and tone
Operating Temperature	0 ~ 40 °C
Operating Humidity	Less than 80% RH
Altitude	2000m maximum
For Indoor Use Only	√
Pollution Degree	2
Power Source	1.5V (AAA) x 1
Dimensions	142 (L) x 28 (W) x 27 (D) mm
Weight	Approx. 39g (battery included)



Ordering Information:

- BST-VT107: Non-Contact Low Voltage Detector with Adjustable Sensitivity.

Test Equipment Depot - 800.517.8431
 99 Washington Street Melrose, MA 02176
 TestEquipmentDepot.com

**Safety Standard:**

- EN 61010-1 CAT IV 1000V, EN 61326-1