

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wire-Nut® Wire Connectors				
Model	300 Volt Maximum		600 Volt Maximum	
71B® Strip solid wires ¼" (6.5mm) Str p stranded wires 5/16" (8mm)	1 #14	1 #16 w/1 to 3 #22		
	1 or 2 #16	1 #16 w/1 #20 w/1 #18 or #20		
	1 #18 str	1 #18 w/1 to 3 #20		
	2 or 3 #18	1 #18 w/1 to 4 #22		
	2 or 4 #20	1 or 2 #18 w/1 #20 w/1 #22		
	2 #22 str	2 #18 w/1 #20		
	3 or 4 #22	2 #18 w/1 or 2 #22		
5 #22 sol	1 #20 w/1 to 4 #22			
1 #14 w/1 #20 or #22	2 #20 w/1 to 3 #22			
1 #16 w/1 #18	3 #20 w/1 or 2 #22			
1 #16 w/1 or 2 #20	4 #20 w/1 #22			
Model	300 Volt Maximum		600 Volt Maximum	
72B® Str p wires #16 and smaller ½" (13mm) all others 3/8" (9.5mm)	1 #14 str	1 #16 w/1 to 4 #20 or #22		
	1 #16 str	1 #16 w/1 #22 w/1 #18 or #20		
	2 or 3 #16	2 #16 w/1 #18		
	1 #18 str	2 #16 w/1 or 2 #20		
	2 to 4 #18	2 #16 w/1 #20 w/1 #22		
	2 to 5 #20	2 #16 w/1 to 3 #22		
	2 #22	1 #18 w/1 to 4 #20 or #22		
	1 #14 w/1 #16	1 or 2 #18 w/1 #20 w/1 #22 2		
	1 #14 w/1 or 2 #18	#18 w/1 to 3 #20 or #22		
	1 #14 w/1 to 3 #20	3 #18 w/1 or 2 #20 or #22		
	1 #14 w/1 to 4 #22	4 #18 w/1 #20 or #22		
1 #16 w/1 to 3 #18	3 #20 w/1 or 2 #22			
1 #16 w/1 #18 w/1 #20	4 #20 w/1 #22			
Model	300 Volt Maximum		600 Volt Maximum	
73B® Str p wires #16 and smaller Stranded 3/8" (9.5mm) all others 5/16" (8mm)	3 or 4 #16	3 #16 w/1 #18	1 or 2 #14	2 #16 w/1 to 3 #22
	5 #18	3 #16 w/1 or 2 #20 or #22	1 #16 str	2 #16 w/1 #18
	3 to 5 #20	4 #16 w/1 #20 or #22	2 #16	1 or 2 #16 w/1 #20 w/1 #22
	5 #22	1 #18 w/1 #20	1 #18 str	1 #16 w/1 #18 w/1 #22
	1 #14 w/2 #16	1 #18 str w/5 #22 str	2 or 4 #18	1 #18 w/2 to 4 #20
	1 #14 w/1 #16 w/1 #18	2 #18 w/3 #22	1 #14 w/1 or 2 #18	1 #18 w/3 or 4 #22
	1 #14 w/3 #18	3 #18 w/2 #20 or #22	1 #14 w/1 to 3 #20	1 or 2 #18 w/1 #20 w/1 #22
	1 #14 w/4 #20	4 #18 w/1 #20 or #22	1 #14 w/1 to 3 #22	2 #18 w/1 or 2 #20
	2 #14 w/1 #18	1 #20 w/4 #22	1 #14 w/1 #16 w/1 #18	2 #18 w/1 to 3 #22
	2 #14 w/1 to 3 #20 or #22	2 #20 w/2 or 3 #22	1 #14 w/1 #16	3 #18 w/1 #20 or #22
	1 #16 w/4 #18	3 #20 w/1 or 2 #22	1 #16 w/1 or 2 #18	
	2 #16 w/2 or 3 #18	4 #20 w/1 #22	1 #16 w/1 to 3 #20 or #22	
	2 #16 w/3 #20		2 #16 w/1 or 2 #20	

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wire-Nut® Wire Connectors			
Model	300 Volt Maximum	600 Volt Maximum	
74B® Strip #16 and smaller 7/16" (11.5mm) all others 3/8" (9.5mm)	1 #10 w/2 #12	1 #8 1 #10 1 to 3 #12 1 to 4 #14 2 to 5 #16 2 to 5 #18 3 to 6 #20 1 #10 w/1 #12 1 #10 w/1 or 2 #14 #16 or #18 1 #10 w/3 or 4 #16 or #18 1 #10 w/1 #12 w/1 #14 or #16 1 #10 w/1 #12 w/1 or 2 #18 1 #10 w/1 #14 w/2 #16 1 #10 w/1 #14 w/1 to 3 #18 1 #10 w/2 #14 w/1 #16 1 #10 w/1 #16 w/1 or 2 #18 1 #12 w/1 to 3 #14 #16 or #18 1 #12 w/4 #16 or #18 1 #12 w/1 #14 w/3 #16 1 #12 w/2 #14 w/2 #16 2 #12 w/1 or 2 #14 2 #12 w/1 or 2 #16 or #18 2 #12 w/1 #14 w/1 #16 or #18 2 #12 w/1 #16 w/1 or 2 #18 1 #14 w/1 to 4 #16 #18 or #20 1 #14 w/1 #16 w/1 to 3 #20	1 #14 w/1 #18 w/1 to 3 #20 2 #14 w/1 to 3 #16 #18 or #20 2 #14 w/1 #16 w/1 or 2 #18 or #20 2 #14 w/1 #16 w/1 to 3 #22 3 #14 w/1 #16 w/1 #18 #20 or #22 3 #14 w/1 #18 w/1 #20 or #22 3 #14 w/1 or 2 #16 3 #14 w/1 or 2 #18 or #20 4 #14 w/1 #16 or #18 1 #16 w/1 #18 w/2 or 3 #20 or #22 1 #16 w/1 #18 w/3 or 4 #22 1 #16 w/2 #20 w/2 #22 1 #16 w/1 to 4 #18 #20 or #22 2 #16 w/1 to 3 #18 #20 or #22 2 #16 w/1 #18 w/1 or 2 #20 or #22 3 #16 w/1 or 2 #18 #20 or #22 3 #16 w/1 #18 w/1 #20 or #22 4 #16 w/1 or 2 #18 #20 or #22 1 #18 w/3 or 4 #20 or #22 1 #18 w/2 #20 w/3 #22 2 #18 w/3 #20 or #22 2 #18 w/1 #20 w/3 #22

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wire-Nut® Wire Connectors				
Model	300 Volt Maximum		600 Volt Maximum	
76B® Strip wires #16 and smaller 1/2" (13mm); all others 7/16" (11.5mm)	2 #8 str		1 #6 or #8	2 #12 w/1 or 2 #16 or #18
	3 #10		1 or 2 #10	2 #12 w/1 or 2 #20 w/1 or 2 #22
	5 #12		1 to 4 #12	2 #12 w/1 #18 w/1 to 3 #20 or #22
	1 #6 w/1 or 2 #16		2 to 5 #14	2 #12 w/1 #16 w/1 to 3 #20 or #22
	1 #6 w/1 #14		4 to 6 #16	2 #12 w/1 #16 w/1 to 3 #18
	1 #6 w/1 #12		1 #8 w/1 to 3 #16	2 #12 w/1 #14 w/1 to 3 #18 or #16
	1 #6 w/1 #14 w/1 to 4 #22		1 #8 w/1 or 2 #14	3 #12 w/1 #18 w/1 or 2 #22 or #20
	1 #6 w/1 #14 w/1 or 2 #18		1 #8 w/1 #12	3 #12 w/1 #16 w/1 or 2 #22 or #20
	1 #6 w/1 #14 w/1 #16		1 #8 w/1 #14 w/1 to 4 #20	3 #12 w/1 #16 w/1 or 2 #18
	1 #8 w/4 #16		1 #8 w/1 to 4 #18 #20 or #22	3 #12 w/1 #14
	1 #8 w/3 #14		1 #8 w/1 #14 w/1 or 2 #16	3 #12 w/1 #14 w/1 #20
	1 #8 w/2 #12		1 #8 w/1 #12 w/1 #16 or #18	3 #12 w/1 #14 w/1 or 2 #22
	1 #8 w/1 #10		1 #10 w/1 to 4 #16 #18 #20 or #22	3 #12 w/1 #14 w/1 #18
	1 #8 w/1 #14 w/4 #18		1 #10 w/5 #16	3 #12 w/1 or 2 #20 or #22
	1 #8 w/1 #14 w/3 or 4 #16		1 #10 w/1 to 3 #14	3 #12 w/1 to 3 #18
	1 #8 w/1 #12 w/1 to 4 #16 or #18		1 #10 w/1 or 2 #12	3 #12 w/1 or 2 #16
	1 #8 w/1 #12 w/1 or 2 #14		1 #10 w/1 or 2 #20 w/1 to 3 #22	3 #12 w/1 #20 w/1 or 2 #22
	1 #8 w/2 #12 w/1 or 2 #18		1 #10 w/1 #18 w/1 to 4 #20 or #22	3 #12 w/2 #20 w/1 #22
	1 #8 w/2 #12 w/1 #14 or #16		1 #10 w/1 #16 w/1 to 4 #20 or #22	1 #14 w/3 or 4 #18
	1 #8 w/1 #10 w/1 #12 or #14		1 #10 w/1 #16 w/1 to 4 #18	1 #14 w/1 #20 w/3 or 4 #22
	1 #10 w/4 #14		1 #10 w/1 #16 w/1 to 4 #18	1 #14 w/1 #18 w/4 #22
	1 #10 w/3 #12		1 #10 w/1 #14 w/1 to 4 #18 #20 or #22	1 #14 w/1 #18 w/3 or 4 #20
	1 #10 w/2 #14 w/3 #16		1 #10 w/1 #14 w/1 to 4 #16	1 #14 w/1 #16 w/2 or 4 #20
	1 #10 w/1 #12 w/4 #16		1 #10 w/2 #14 w/1 or 2 #16	1 or 2 #14 w/1 #16 w/1 to 3 #18
	1 #10 w/1 #12 w/3 or 4 #14		1 #10 w/1 #12 w/1 to 4 #18	2 #14 w/2 or 4 #16
	1 #10 w/2 #12 w/2 or 3 #16 or #18		1 #10 w/1 #12 w/1 to 3 #16	2 #14 w/1 or 2 #20 w/1 or 2 #22 2
	1 #10 w/2 #12 w/1 or 2 #14		1 #10 w/1 #12 w/1 to 3 #16	#14 w/1 #18 w/1 to 3 #20 or #22
	2 #10 w/3 #16		1 #10 w/1 #12 w/1 or 2 #14	2 #14 w/1 #16 w/1 to 3 #20 or #22
	2 #10 w/2 or 3 #14		1 #10 w/2 #12 w/1 #16 or #18	3 #14 w/1 or 2 #16 #18 #20 or #22
	2 #10 w/1 or 2 #12		2 #10 w/1 to 3 #18	#22
	2 #10 w/1 #16 w/2 or 3 #18		2 #10 w/2 #16	3 #14 w/1 #16 w/1 or 2 #18
	2 #10 w/1 #14 w/2 or 3 #20 or #22		2 #10 w/1 #14	3 #14 w/1 #18 w/1 or 2 #20 or #22
	2 #10 w/1 #14 w/1 to 3 #18		2 #10 w/1 #16 w/1 #18	4 #14 w/1 #18 #20 or #22
	2 #10 w/2 #14 w/1 #16		2 #10 w/1 #14 w/1 #20 or #22	4 #14 w/2 #18
	2 #10 w/1 #12 w/1 to 3 #18		1 #12 w/3 or 4 #22	4 #14 w/1 #16
	2 #10 w/1 #12 w/1 or 2 #16		1 #12 w/2 to 4 #18 or #20	5 #14 w/1 #18
	3 #10 w/1 #16 or #18		1 #12 w/1 to 4 #14 or #16	1 #16 w/4 #18
	2 #12 w/1 #14 w/3 #16		1 #12 w/1 #20 w/2 to 4 #22	2 #16 w/3 #20
	2 #12 w/2 #14 w/2 #16		1 #12 w/2 #20 w/1 to 3 #22	2 #16 w/3 or 4 #18
	3 #12 w/2 #14		1 #12 w/ #18 w/1 to 4 #20 or #22	2 #16 w/1 #20 w/3 #22
	3 #12 w/3 #16		1 #12 w/1 #16 w/1 to 4 #20 or #22	2 #16 w/2 #20 w/2 #22
	3 #12 w/1 #16 w/2 #18		1 #12 w/1 #16 w/1 to 4 #18	2 #16 w/1 #18 w/3 #22
	3 #12 w/1 #14 w/1 or 2 #16		1 #12 w/1 #14 w/1 to 4 #16 #18	2 #16 w/1 #18 w/2 or 3 #20
	3 #12 w/2 #14 w/1 #16		#20 or #22	3 #16 w/1 or 2 #18 #20 or #22
	4 #12 w/1 #14 #16 #18 #20 or #22		1 #12 w/2 #14 w/1 to 3 #16	3 #16 w/1 or 2 #20 w/1 #22
			2 #12 w/2 #14 w/1 #16	3 #16 w/1 #18 w/1 or 2 #20 or #22
			2 #12 w/1 to 3 #14	4 #16 w/1 or 2 #22
		2 #12 w/1 #14 w/1 to 3 #20 or #22	4 #16 w/1 #18 or #20	
		2 #12 w/1 to 3 #20 or #22	4 or 5 #16 w/1 #22	

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wire-Nut® Connectors				
Model	600 Volt Maximum			
59B® Strip wires 1/2" (13mm)	1 #12	1 #14 w/1 #18 w/1 or 2 #22	2 #16 w/1 to 4 #18 #20 or #22	2 #18 w/1 to 4 #20 or #22
	1 to 3 #14	1 #14 w/1 #16 w/1 #20 or #22	2 #16 w/1 #20 w/1 or 2 #22 2	2 #18 w/1 #20 w/1 or 2 #22
	2 to 4 #16	2 #14 w/1 to 4 #20 or #22	#16 w/1 #18 w/1 or 2 #22 3	3 #18 w/1 to 3 #20 or #22
	2 to 6 #18	2 #14 w/1 or 2 #18	#16 w/1 to 3 #20 or #22	3 #18 w/1 #20 w/1 or 2 #22
	2 to 6 #20	2 #14 w/1 #16	3 #16 w/1 or 2 #18	4 #18 w/1 or 2 #22 or #20
	4 to 6 #22	2 #14 w/1 #20 w/1 or 2 #22	3 #16 w/1 #20 w/1 or 2 #22	4 #18 w/1 #20
	1 #12 w/1 to 3 #18	2 #14 w/1 #18 w/1 or 2 #22	3 #16 w/1 #18 w/1 or 2 #22	5 #18 w/1 #20 w/1 #22
	1 #12 w/1 or 2 #16	2 #14 w/1 #16 w/1 #20 or #22	4 #16 w/1 or 2 #22	1 #20 w/2 to 5 #22
	1 #12 w/1 #14	1 #16 Stranded OR 1 #18 Str 1	4 #16 w/1 #18 or #20	2 #20 w/1 to 4 #22
	1 #14 w/1 to 5 #18 #20 or #22	#16 w/1 to 5 #18 #20 or #22 1	4 #16 w/1 #20 w/1 #22	3 #20 w/1 to 3 #22
	1 #14 w/1 to 3 #16	#16 w/1 #20 w/1 or 2 #22 1	1 #18 w/1 to 4 #20 or #22	4 #20 w/1 or 2 #22
	1 #14 w/1 #20 w/1 or 2 #22	#16 w/1 #18 w/1 or 2 #22	1 #18 w/1 #20 w/1 or 2 #22	5 #20 w/1 #22
IDEAL Wing-Nut® Wire Connectors				
Model	600 Volt Maximum			
451® Strip wires 3/8" (9,5mm)	1 #10	1 #10 w/1 or 2 #16	2 #12 w/1 #14	1 #16 w/1 to 5 #18
	1 to 3 #12	1 #10 w/1 to 3 #18	1 #14 w/1 to 5 #18	2 #16 w/1 to 4 #18
	1 to 3 #14	1 #12 w/1 to 5 #18	1 #14 w/1 to 4 #16	3 #16 w/1 to 3 #18
	2 to 4 #16	1 #12 w/1 to 3 #16	2 #14 w/1 to 3 #18	4 #16 w/1 or 2 #18
	2 to 4 #18	1 #12 w/1 or 2 #14	2 #14 w/1 to 3 #16	
	1 #10 w/1 #12	2 #12 w/1 or 2 #18	3 #14 w/1 #16	
	1 #10 w/1 or 2 #14	2 #12 w/1 #16	3 #14 w/1 or 2 #18	
Model	600 Volt Maximum			
452® Strip wires 1/2" (13mm)	1 #6	1 #10 w/2 #12 w/1 to 3 #16	2 #12 w/1 to 4 #18 #16 or #14	2 #16 w/1 #18 w/1 to 3 #22
	1 or 2 #8	1 #10 w/2 #12 w/1 to 3 #18	3 #12 w/1 to 3 #18 #16 or #14	2 #16 w/1 #18 w/1 to 3 #20
	1 to 4 #10	1 #10 w/2 #12 w/1 or 2 #14	3 #12 w/1 #16 w/1 or 2 #18	2 #16 w/1 to 4 #22 #20 or #18
	1 to 5 #12	1 #10 w/3 #12 w/1 #14	3 #12 w/1 #14 w/1 or 2 #18	3 #16 w/1 to 3 #22 #20 or #18
	1 to 6 #14 #16	2 #10 w/1 to 4 #18 or #16	3 #12 w/1 #14 w/1 or 2 #16	3 #16 w/1 or 2 #22 w/1 #20
	2 to 6 #18	2 #10 w/1 to 3 #14 or #12	3 #12 w/2 #14 w/1 #16	3 #16 w/1 #18 w/1 or 2 #22
	3 to 6 #20	2 #10 w/1 #16 w/1 to 3 #18	4 #12 w/1 or 2 #16	3 #16 w/1 #18 w/1 or 2 #20
	4 to 6 #22	2 #10 w/2 #14 w/1 or 2 #16	4 #12 w/1 #14	4 #16 w/1 or 2 #22 #20 or #18
	1 #6 w/1 or 2 #12	2 #10 w/1 #12 w/1 to 3 #16	4 #12 w/1 #16 w/1 #18	4 #16 w/1 #22 w/1 #20
	1 #6 w/1 #10	2 #10 w/1 #12 w/1 or 2 #14	4 #12 w/1 #14 w/1 #18 or #16	4 #16 w/1 #18 w/1 #22
	1 #6 w/2 #14 w/1 or 2 #16	2 #10 w/2 #12 w/1 or 2 #18	1 #14 w/1 to 5 #22 or #20	4 #16 w/1 #18 w/1 #20
	1 #6 w/1 #12 w/1 or 2 #14	2 #10 w/2 #12 w/1 or 2 #16	1 #14 w/1 to 5 #18 or #16	5 #16 w/1 #22 #20 or #18
	1 #6 w/2 #12 w/1 #18	2 #10 w/2 #12 w/1 #14	1 #14 w/1 #16 w/1 to 3 #18	1 #18 w/1 to 5 #22 or #20
	1 #6 w/1 #10 w/1 #14	3 #10 w/1 to 3 #18 3 #10 w/1 to 3 #16	2 #14 w/1 #16 w/1 to 3 #18	1 #20 w/1 #22 w/1 to 3 #18
	1 #8 w/1 to 5 #16	3 #10 w/1 or 2 #14	2 #14 w/1 to 4 #22 or #20	1 #20 w/2 #22 w/1 to 3 #18
	1 #8 w/1 to 4 #14	3 #10 w/1 #12	2 #14 w/1 to 4 #18 or #16	2 #20 w/1 #22 w/1 to 3 #18
	1 #8 w/1 to 3 #12	3 #10 w/1 #12	3 #14 w/1 to 3 #22 or #20	2 #18 w/1 to 4 #22 #20
	1 #8 w/2 #12 w/1 or 2 #14	3 #10 w/1 #16 w/1 or 2 #18	3 #14 w/1 to 3 #18 or #16	3 #18 w/1 to 3 #22 or #20
	1 #8 w/1 or 2 #10	3 #10 w/1 #14 w/1 or 2 #18	3 #14 w/1 #16 w/1 or 2 #18	4 #18 w/1 or 2 #22 or #20
	1 #8 w/1 #10 w/1 or 2 #14	3 #10 w/1 #14 w/1 #16	4 #14 w/1 or 2 #22	5 #18 w/1 #22 or #20
	#12	3 #10 w/1 #12 w/1 #18	4 #14 w/1 or 2 #20 #18 or #16	1 #20 w/2 to 5 #22
	1 #8 w/2 #10 w/1 #14	3 #10 w/1 #12 w/1 #16	4 #14 w/1 #16 w/1 #18	2 #20 w/1 to 4 #22
	1 #10 w/1 to 5 #18 #16 or #14	1 #12 w/1 to 5 #18 #16 or #14	5 #14 w/1 #18 or #16	3 #20 w/1 to 3 #22
	1 #10 w/1 to 4 #12	1 #12 w/1 #16 w/1 to 3 #18	1 #16 w/1 to 5 #22 #20 or #18	4 #20 w/1 or 2 #22
	1 #10 w/1 #16 w/1 to 4 #18	1 #12 w/1 #14 w/1 to 3 #18	1 #16 w/1 #20 w/1 or 2 #22	5 #20 w/1 #22
	1 #10 w/1 #14 w/1 to 4 #16 or #18	1 or 2 #12 w/1 #14 w/1 to 3 #16	1 #16 w/2 #20 w/1 or 2 #22	
	1 #10 w/2 #14 w/1 to 3 #16	1 #12 w/2 #14 w/1 or 2 #16	1 #16 w/1 #18 w/1 to 3 #22	
	1 #10 w/1 #12 w/1 to 4 #14	2 #12 w/1 #14 w/1 to 3 #18	1 #16 w/1 #18 w/1 to 3 #20	
	1 #10 w/1 #12 w/1 to 4 #16 or #18	2 #12 w/1 #16 w/1 to 3 #18	2 #16 w/1 #20 w/1 or 2 #22 2	
	1 #10 w/1 #12 w/1 to 4 #16 or #18	2 #12 w/2 #14 w/1 or 2 #16	#16 w/2 #20 w/1 or 2 #22	

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Wing-Nut® Wire Connectors				
Model	600 Volt Maximum			
454® Strip wires 7/8"	1 or 2 #6	2 #6 w/1 #14 or #12	1 #8 w/1 #12 w/1 to 4 #14	1 #10 w/1 #12 w/1 to 4 #14
	2 or 3 #8	1 #6 w/1 #12 w/1 to 4 #14	1 #8 w/2 #12 w/1 to 3 #14	1 #10 w/2 #12 w/1 to 3 #14
	2 to 5 #10	1 #6 w/2 #12 w/1 to 3 #14	1 #8 w/3 #12 w/1 or 2 #14	1 #10 w/3 #12 w/1 or 2 #14
	3 to 6 #12	1 #6 w/3 #12 w/1 or 2 #14	1 #8 w/4 #12 w/1 #14	1 #10 w/4 #12 w/1 #14
	5 or 6 #14	1 #6 w/4 #12 w/1 #14	1 #8 w/1 #10 w/1 to 4 #14	1 #10 w/2 to 4 #12
	1 #8 w/1 to 5 #14 or #12	1 #6 w/1 #10 w/1 to 4 #14	1 #8 w/1 #10 w/1 to 4 #12	2 #10 w/1 #12 w/1 to 3 #14
	1 #8 w/1 to 4 #10	1 #6 w/1 #10 w/1 to 3 #12	1 #8 w/2 #10 w/1 to 3 #14	2 #10 w/2 #12 w/1 or 2 #14
	1 #10 w/3 to 5 #14	1 #6 w/2 #10 w/1 or 2 #14	1 #8 w/2 #10 w/1 to 3 #12	2 #10 w/3 #12 w/1 #14
	1 #12 w/4 or 5 #14	1 #6 w/2 #10 w/1 #12	1 #8 w/3 #10 w/1 or 2 #14	2 #10 w/1 to 4 #14 or #12
	2 #12 w/2 to 4 #14	1 #6 w/1 #8 w/1 to 3 #14	1 #8 w/3 #10 w/1 #12	3 #10 w/1 #12 w/1 or 2 #14
	3 #12 w/1 to 3 #14	1 #6 w/1 #8 w/1 or 2 #12	2 #8 w/1 #12 w/1 to 3 #14	3 #10 w/2 #12 w/1 #14
	4 #12 w/1 #14	1 #6 w/1 #8 w/1 #10	2 #8 w/2 #12 w/1 or 2 #14	3 #10 w/1 to 3 #14
	1 #6 w/1 to 4 #14	2 #8 w/1 to 4 #14	2 #8 w/3 #12 w/1 #14	3 #10 w/1 to 3 #12
	1 #6 w/1 to 5 #12	2 #8 w/1 to 3 #12	2 #8 w/1 #10 w/1 to 3 #14	4 #10 w/1 #14 w/1 #12
	1 #6 w/1 to 3 #10	2 #8 w/1 or 2 #10	2 #8 w/1 #10 w/1 or 2 #12	
	1 #6 w/1 or 2 #8	3 #8 w/1 or 2 #14	2 #8 w/2 #10 w/1 #14 sol	
	IDEAL Greenie® Grounding Wire Connectors			
Model	600 Volt Maximum			
92® Strip wires 1"	2 to 4 #12	1 or 2 #12 w/1 to 3 #14		
	2 to 4 #14	3 #12 w/1 #14		
	1 #10 w/1 or 2 #12			
	1 #10 w/1 to 3 #14			
IDEAL Twister® Wire Connectors				
Model	600 Volt Maximum			
340® Strip wires #22 #18 3/8"; Strip wires #16 #10 7/16"	2 to 5 #22	2 #18 w/1 to 3 #20 or #22	4 #16 w/1 or 2 #18	1 #12 w/1 to 5 #18
	2 to 5 #20	3 #18 w/1 or 2 #20 or #22	1 #14 w/1 to 4 #22	1 #12 w/1 to 3 #16
	2 to 5 #18	4 #18 w/1 #20 or #22	1 #14 w/1 to 3 #20	1 #12 w/1 or 2 #14
	2 to 4 #16	1 #16 w/1 to 4 #20 or #22	1 #14 w/1 to 5 #18	2 #12 w/1 or 2 #18
	1 to 3 #14 or #12	1 #16 w/1 to 5 #18	1 #14 w/1 to 4 #16	2 #12 w/1 #14 or #16
	1 #10	2 #16 w/1 to 3 #22 or #20	2 #14 w/1 to 3 #16 #18 #20 or #22	1 #10 w/1 to 3 #18
	3 #20 w/1 or 2 #22	2 #16 w/1 to 4 #18	3 #14 w/1 or 2 #18	1 #10 w/1 or 2 #14 or #16
	4 #20 w/1 #22	3 #16 w/1 to 3 #18 #20 or #22	3 #14 w/1 #16	1 #10 w/1 #12
	1 #18 w/1 to 4 #20 or #22	4 #16 w/1 #20 or #22		
	341® Strip wires 1/2"	1 to 3 #10	3 #14 w/2 #12	3 #18 w/1 or 2 #10
1 to 3 #12		4 #14 w/1 #12 or #10	4 #18 w/1 or 2 #16 #14 or #12	1 #22 w/1 #20 w/1 or 2 #16
4 #12 sol		1 #16 w/1 to 4 #14 or #12	4 #18 w/1 #10	1 #14 w/1 or 2 #12 w/1 #10
1 to 5 #14		1 #16 w/1 or 2 #10	5 #18 w/1 #16 or #14	2 #14 w/1 #12 w/1 #10
1 #16 str		2 #16 w/1 to 4 #14	1 #20 w/1 to 4 #18 #16 or #14	1 #16 w/1 #12 w/1 #10
2 to 6 #16		2 #16 w/1 to 3 #12	2 #20 w/1 to 3 #18 #16 or #14	2 #16 w/1 #14 w/1 or 2 #12
2 to 6 #18		2 #16 w/1 or 2 #10	3 #20 w/1 or 2 #18 #16 or #14	2 #16 w/2 #14 w/1 #12
2 or 6 #20		3 #16 w/1 to 3 #14	4 #20 w/1 or 2 #18 #16 or #14	2 #16 w/1 #12 w/1 #10
1 #10 w/1 #8		3 #16 w/1 or 2 #12 or #10	3 to 6 #22	3 #16 w/1 #14 w/1 #12 or #10
1 #12 w/1 or 2 #10		4 #16 w/1 or 2 #14 or #12	1 #22 sol w/1 #20 sol	4 #16 w/1 #12 w/1 #10
1 #12 w/1 #8		4 #16 w/1 #10	1 #22 w/2 to 5 #20	1 #18 w/1 to 4 #16 #14 or #12
2 #12 w/1 #10		5 #16 w/1 #14	1 #22 w/1 to 5 #18 or #16	5 #16 sol w/1 #10 sol
1 #14 str w/1 or 2 #12 str		2 #18 w/1 to 4 #16 or #14	2 #22 w/1 to 4 #20 #18 or #16	1 #16 w/1 or 2 #14 w/1 #12 or
1 #14 sol w/1 to 3 #12		3 #18 w/1 to 3 #12	3 #22 w/1 to 3 #20 #18 or #16	#10
1 #14 w/1 or 2 #10		2 #18 w/1 or 2 #10	4 #22 w/1 or 2 #20 #18 or #16	
2 #14 w/1 or 2 #12 or #10		3 #18 w/1 to 3 #16 #14 or #12		
2 #14 w/1 #8				
3 #14 w/1 #12 or #10				

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Twister® Wire Connectors				
Model	600 Volt Maximum			
342® Strip wires 5/8"	1 or 2 #8	4 #12 w/1 #10	1 #16 w/1 to 3 #10	1 #14 w/3 #12 w/1 #10
	2 to 4 #10	1 #14 w/1 to 4 #12	2 #16 w/1 to 4 #14 or #12	1 #14 w/1 #10 w/1 #8
	2 to 6 #12	1 #14 w/1 to 3 #10	2 #16 w/1 or 2 #10	2 #14 w/1 #12 w/1 or 2 #10
	3 to 6 #14	1 #14 w/1 or 2 #8	3 #16 w/1 to 3 #14	2 #14 w/1 #12 w/1 #8
	1 #8 w/1 #6	1 or 2 #14 w/1 #6	3 #16 w/1 or 2 #12 or #10	2 #14 w/2 #12 w/1 #10
	1 #10 w/1 or 2 #8	2 #14 w/1 to 3 #12	4 #16 w/1 or 2 #14 or #12	2 #14 w/1 #10 w/1 #8
	2 #10 w/1 #8	2 #14 w/1 to 3 #10	4 #16 w/1 #10	3 #14 w/1 #10 w/1 #8
	1 #12 w/1 or 2 #10	2 #14 w/1 #8	3 #18 w/3 #16 or #14	1 #16 w/1 #14 w/1 or 2 #12
	1 #12 w/3 #10	3 #14 w/1 to 3 #12 or #10	3 #18 w/1 or 2 #12 or #10	2 #16 w/1 #14 w/1 or 2 #12
	1 #12 w/1 or 2 #8	3 or 4 #14 w/1 #8	4 #18 w/1 or 2 #16 #14 or #12	2 #16 w/2 #14 w/1 #12 or #10
	1 or 2 #12 w/1 #6	3 #14 w/1 #6	5 #18 w/1 #16 #14 #12 or #10	2 #16 w/1 #12 w/1 #10
	2 #12 w/1 or 2 #10	4 #14 w/1 or 2 #12 or #10	1 #12 w/1 #10 w/1 #8	3 #16 w/1 #14 w/1 or 2 #12
	2 #12 w/1 #8 or #6	4 #14 w/1 #6	1 #14 w/1 #12 w/1 or 2 #10	3 #16 w/1 #14 w/1 #10
	2 #12 w/2 #8	5 #14 w/1 #12 or #10	1 #14 w/1 #12 w/1 #8 or #6	4 #16 w/1 #14 w/1 #12
	3 #12 w/1 #10 or #8	5 #14 w/1 #8	1 #14 w/2 #12 w/1 or 2 #10	
	3 #12 w/2 #10	1 #16 w/2 to 5 #14 or #12	1 #14 w/2 #12 w/1 #8	
	343® Strip wires 7/16" (11mm) For capping off single 14 12 or 10 AWG conductors strip wires ¼"	2 to 6 #22 AWG	3 #18 AWG with 1 or 2 #20	1 #14 AWG with 1 to 4 #22 AWG
2 to 6 #20 AWG		AWG or #22 AWG	1 #14 AWG with 1 to 3 #20 AWG	AWG
2 to 5 #18 AWG		4 #18 AWG with 1 #20 AWG or	1 #14 AWG with 1 to 5 #18 AWG	1 #12 AWG with 1 or 2 #14
2 to 4 #16 AWG		#22 AWG	1 #14 AWG with 1 to 4 #16 AWG	AWG
1 to 3 #14 AWG		1 #16 AWG with 1 to 4 #20	2 #14 AWG with 1 to 3 #20 AWG or #22	2 #12 AWG with 1 or 2 #18
1 to 3 #12 AWG		AWG or #22 AWG	AWG	AWG
4 #12 AWG SOL D		1 #16 AWG with 1 to 5 #18	2 #14 AWG with 1 to 3 #18 AWG	2 #12 AWG with 1 #16 AWG
1 #10 AWG		AWG	2 #14 AWG with 1 to 3 #16 AWG	2 #12 AWG with 1 #14 AWG
3 #20 AWG with 1 or 2 #22		2 #16 AWG with 1 to 3 #22	3 #14 AWG with 1 or 2 #18 AWG	1 #10 AWG with 1 to 3 #18
AWG		AWG	3 #14 AWG with 1 #16 AWG	AWG
4 #20 AWG with 1 #22		2 #16 AWG with 1 to 3 #20	1 #12 AWG with 1 to 5 #18 AWG	1 #10 AWG with 1 or 2 #16
AWG		AWG		AWG
1 # 18 AWG with 1 to 4 #20	2 #16 AWG with 1 to 4 # 18		1 #10 AWG with 1 or 2 #14	
AWG or # 22 AWG	AWG		AWG	
2 #18 AWG with 1 to 3 #20	3 #16 AWG with 1 to 3 #18		1 #10 AWG with 1 #12 AWG	
AWG or #22 AWG	AWG or #20 AWG or #22 AWG			
	4 #16 AWG with 1 #20 AWG or			
	#22 AWG			
	4 #16 AWG with 1 or 2 #18			
	AWG			

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Twister® Wire Connectors				
Model	600 Volt Maximum			
344® Strip wires 1/2" (13mm)	1 #6	1 #10 w/2 #12 w/1 to 3 #16	2 #12 w/1 to 4 #18 #16 or #14	2 #16 w/1 #18 w/1 to 3 #22
	1 or 2 #8	1 #10 w/2 #12 w/1 to 3 #18	3 #12 w/1 to 3 #18 #16 or #14	2 #16 w/1 #18 w/1 to 3 #20
	1 to 4 #10	1 #10 w/2 #12 w/1 or 2 #14	3 #12 w/1 #16 w/1 or 2 #18	2 #16 w/1 to 4 #22 #20 or #18
	1 to 5 #12	1 #10 w/3 #12 w/1 #14	3 #12 w/1 #14 w/1 or 2 #18	3 #16 w/1 to 3 #22 #20 or #18
	1 to 6 #14 #16	2 #10 w/1 to 4 #18 or #16	3 #12 w/1 #14 w/1 or 2 #16	3 #16 w/1 or 2 #22 w/ 1 #20
	2 to 6 #18	2 #10 w/1 to 3 #14 or #12	3 #12 w/2 #14 w/1 #16	3 #16 w/1 #18 w/1 or 2 #22
	3 to 6 #20	2 #10 w/1 #16 w/1 to 3 #18	4 #12 w/1 or 2 #16	3 #16 w/1 #18 w/1 or 2 #20
	4 to 6 #22	2 #10 w/2 #14 w/1 or 2 #16	4 #12 w/1 #14	4 #16 w/1 or 2 #22 #20 or #18
	1 #6 w/1 or 2 #12	2 #10 w/1 #12 w/1 to 3 #16	4 #12 w/1 #16 w/1 #18	4 #16 w/1 #22 w/1 #20
	1 #6 w/1 #10	2 #10 w/1 #12 w/1 or 2 #14	4 #12 w/1 #14 w/1 #18 or #16	4 #16 w/1 #18 w/1 #22
	1 #6 w/2 #14 w/1 or 2 #16	2 #10 w/2 #12 w/1 or 2 #18	1 #14 w/1 to 5 #22 or #20	4 #16 w/1 #18 w/1 #20
	1 #6 w/1 #12 w/1 or 2 #14	2 #10 w/2 #12 w/1 or 2 #16	1 #14 w/1 to 5 #18 or #16	5 #16 w/1 #22 #20 or #18
	1 #6 w/2 #12 w/1 #18	2 #10 w/2 #12 w/1 #14	1 #14 w/1 #16 w/1 to 3 #18	1 #18 w/1 to 5 #22 or #20
	1 #6 w/1 #10 w/ 1 #14	3 #10 w/1 to 3 #18 3 #10 w/1 to 3 #16	2 #14 w/1 #16 w/1 to 3 #18	1 #20 w/1 #22 w/ 1 to 3 #18
	1 #8 w/1 to 5 #16	3 #10 w/1 or 2 #14	2 #14 w/1 to 4 #22 or #20	1 #20 w/2 #22 w/ 1 to 3 #18
	1 #8 w/1 to 4 #14	3 #10 w/1 #12	2 #14 w/1 to 4 #18 or #16	2 #20 w/1 #22 w/ 1 to 3 #18
	1 #8 w/1 to 3 #12	3 #10 w/1 #16 w/1 or 2 #18	3 #14 w/1 to 3 #22 or #20	2 #18 w/1 to 4 #22 #20
	1 #8 w/2 #12 w/1 or 2 #14	3 #10 w/1 #14 w/1 or 2 #18	3 #14 w/1 to 3 #18 or #16	3 #18 w/1 to 3 #22 or #20
	1 #8 w/1 or 2 #10	3 #10 w/1 #14 w/1 #16	3 #14 w/1 #16 w/1 or 2 #18	4 #18 w/1 or 2 #22 or #20
	1 #8 w/1 #10 w/1 or 2 #14 #12	3 #10 w/1 #12 w/1 #18	4 #14 w/1 or 2 #22	5 #18 w/1 #22 or #20
	1 #8 w/2 #10 w/1 #14	3 #10 w/1 #12 w/1 #16	4 #14 w/1 or 2 #20 #18 or #16	1 #20 w/2 to 5 #22
	1 #10 w/1 to 5 #18 #16 or #14	1 #12 w/1 to 5 #18 #16 or #14	4 #14 w/1 #16 w/1 #18	2 #20 w/1 to 4 #22
	1 #10 w/1 to 4 #12	1 #12 w/1 #16 w/1 to 3 #18	5 #14 w/1 #18 or #16	3 #20 w/1 to 3 #22
	1 #10 w/1 #16 w/1 to 4 #18	1 #12 w/1 #14 w/1 to 3 #18	1 #16 w/1 to 5 #22 #20 or #18	4 #20 w/1 or 2 #22
	1 #10 w/1 #14 w/1 to 4 #16 or #18	1 or 2 #12 w/1 #14 w/1 to 3 #16	1 #16 w/1 #20 w/1 or 2 #22	5 #20 w/1 #22
	1 #10 w/2 #14 w/1 to 3 #16	1 #12 w/2 #14 w/1 or 2 #16	1 #16 w/2 #20 w/1 or 2 #22	
	1 #10 w/1 #12 w/1 to 4 #14 or #18	2 #12 w/1 #14 w/1 to 3 #18	1 #16 w/1 #18 w/1 to 3 #22	
	1 #10 w/1 #12 w/1 to 4 #14 or #18	2 #12 w/1 #16 w/1 to 3 #18	1 #16 w/1 #18 w/1 to 3 #20	
		2 #12 w/2 #14 w/1 or 2 #16	2 #16 w/1 #20 w/1 or 2 #22 2 #16 w/2 #20 w/1 or 2 #22	

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Twister® Wire Connectors				
Model	1000 Volt Maximum			
347 Twister® Strip wires 1/2" (13mm); 7/16" (11mm) for 4 #10 AWG Str.	1 #6	1 #10 w/2 #12 w/1 to 3 #16	2 #12 w/1 to 4 #18 #16 or #14	2 #16 w/1 #18 w/1 to 3 #22
	1 or 2 #8	1 #10 w/2 #12 w/1 to 3 #18	3 #12 w/1 to 3 #18 #16 or #14	2 #16 w/1 #18 w/1 to 3 #20
	1 to 4 #10	1 #10 w/2 #12 w/1 or 2 #14	3 #12 w/1 #16 w/1 or 2 #18	2 #16 w/1 to 4 #22 #20 or #18
	1 to 5 #12	1 #10 w/3 #12 w/1 #14	3 #12 w/1 #14 w/1 or 2 #18	3 #16 w/1 to 3 #22 #20 or #18
	1 to 6 #14 #16	2 #10 w/1 to 4 #18 or #16	3 #12 w/1 #14 w/1 or 2 #16	3 #16 w/1 or 2 #22 w/1 #20
	2 to 6 #18	2 #10 w/1 to 3 #14 or #12	3 #12 w/2 #14 w/1 #16	3 #16 w/1 #18 w/1 or 2 #22
	3 to 6 #20	2 #10 w/1 #16 w/1 to 3 #18	4 #12 w/1 or 2 #16	3 #16 w/1 #18 w/1 or 2 #20
	4 to 6 #22	2 #10 w/2 #14 w/1 or 2 #16	4 #12 w/1 #14	4 #16 w/1 or 2 #22 #20 or #18
	1 #6 w/1 or 2 #12	2 #10 w/1 #12 w/1 to 3 #16	4 #12 w/1 #16 w/1 #18	4 #16 w/1 #22 w/1 #20
	1 #6 w/1 #10	2 #10 w/1 #12 w/1 or 2 #14	4 #12 w/1 #14 w/1 #18 or #16	4 #16 w/1 #18 w/1 #22
	1 #6 w/2 #14 w/1 or 2 #16	2 #10 w/2 #12 w/1 or 2 #18	1 #14 w/1 to 5 #22 or #20	4 #16 w/1 #18 w/1 #20
	1 #6 w/1 #12 w/1 or 2 #14	2 #10 w/2 #12 w/1 or 2 #16	1 #14 w/1 to 5 #18 or #16	5 #16 w/1 #22 #20 or #18
	1 #6 w/2 #12 w/1 #18	2 #10 w/2 #12 w/1 #14	1 #14 w/1 #16 w/1 to 3 #18	1 #18 w/1 to 5 #22 or #20
	1 #6 w/1 #10 w/1 #14	3 #10 w/1 to 3 #18 3 #10 w/1	2 #14 w/1 #16 w/1 to 3 #18	1 #20 w/1 #22 w/1 to 3 #18
	1 #8 w/1 to 5 #16	or 3 #16	2 #14 w/1 to 4 #22 or #20	1 #20 w/2 #22 w/1 to 3 #18
	1 #8 w/1 to 4 #14	3 #10 w/1 or 2 #14	2 #14 w/1 to 4 #18 or #16	2 #20 w/1 #22 w/1 to 3 #18
	1 #8 w/1 to 3 #12	3 #10 w/1 #12	3 #14 w/1 to 3 #22 or #20	2 #18 w/1 to 4 #22 #20
	1 #8 w/2 #12 w/1 or 2 #14	3 #10 w/1 #16 w/1 or 2 #18	3 #14 w/1 to 3 #18 or #16	3 #18 w/1 to 3 #22 or #20
	1 #8 w/1 or 2 #10	3 #10 w/1 #14 w/1 or 2 #18	3 #14 w/1 #16 w/1 or 2 #18	4 #18 w/1 or 2 #22 or #20
	1 #8 w/1 #10 w/1 or 2 #14	3 #10 w/1 #14 w/1 #16	4 #14 w/1 or 2 #22	5 #18 w/1 #22 or #20
	#12	3 #10 w/1 #12 w/1 #18	4 #14 w/1 or 2 #20 #18 or #16	1 #20 w/2 to 5 #22
	1 #8 w/2 #10 w/1 #14	3 #10 w/1 #12 w/1 #16	4 #14 w/1 #16 w/1 #18	2 #20 w/1 to 4 #22
	1 #10 w/1 to 5 #18 #16 or #14	1 #12 w/1 to 5 #18 #16 or #14	5 #14 w/1 #18 or #16	3 #20 w/1 to 3 #22
	1 #10 w/1 to 4 #12	1 #12 w/1 #16 w/1 to 3 #18	1 #16 w/1 to 5 #22 #20 or #18	4 #20 w/1 or 2 #22
	1 #10 w/1 #16 w/1 to 4 #18	1 #12 w/1 #14 w/1 to 3 #18	1 #16 w/1 #20 w/1 or 2 #22	5 #20 w/1 #22
	1 #10 w/1 #14 w/1 to 4 #16	1 or 2 #12 w/1 #14 w/1 to 3 #16	1 #16 w/2 #20 w/1 or 2 #22	
	or #18	1 #12 w/2 #14 w/1 or 2 #16	1 #16 w/1 #18 w/1 to 3 #22	
	1 #10 w/2 #14 w/1 to 3 #16	2 #12 w/1 #14 w/1 to 3 #18	1 #16 w/1 #18 w/1 to 3 #20	
	1 #10 w/1 #12 w/1 to 4 #14	2 #12 w/1 #16 w/1 to 3 #18	2 #16 w/1 #20 w/1 or 2 #22	
	1 #10 w/1 #12 w/1 to 4 #16	2 #12 w/2 #14 w/1 or 2 #16	2 #16 w/2 #20 w/1 or 2 #22	
or #18				

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL WeatherProof™ Wire Connectors				
Model	600 Volt Maximum			
61 Strip wires 3/8" Strip wires #18 and smaller 7/16"	1 or 2 #14 1 #16 Str 2 #16 1 to 4 # 18 Str 2 to 4 #18 Sol 2 to 4 #20 1 #14 w/1 #16 1 #14 w/ 1 #16 w/ 1 #18	1 #14 w/1 or 2 #18 1 #14 w/1 to 3 #20 1 #14 w/1 to 3 #22 2 #16 w/ 1 #18 2 #16 w/1 to 3 #22 2 #16 w/1 or 2 #20 1 #16 w/1 or 2 #18 1 #16 w/1 to 3 #22 or #20	3 #18 w/1 #22 or #20 2 #18 w/1 or 2 #22 or #20 1 #18 w/2 to 4 #20 1 #18 w/3 to 4 #22 1 or 2 #16 w/1 #20 w/1 #22 1 or 2 #18 w/1 #20 w/1 #22	
Model	600 Volt Maximum			
62 Strip wires 1/2"	1 or 2 #10 1 to 3 #12 1 to 5 #14 1 to 6 #16 3 to 6 #18 1 #18 w/2 or 3 #16 1 #18 w/1 to 3 #14 or #12 2 #16 w/1 to 4 #14 2 #16 w/1 to 3 #12 1 #16 w/1 to 2 #14 w/1 #10	1 #18 w/1 or 2 #10 2 #18 w/1 to 3 #16 #14 or #12 2 #18 w/1 or 2 #10 3 #18 w/1 or 2 #16 #14 #12 or #10 4 #18 with 1 or 2 #16 or #14 4 #18 w/1 to 2 #12 4 #18 w/1 #10 2 #16 with 1 #10 3 #16 w/1 #12 w/1 #10	3 #16 w/1 or 2 #14 or #12 3 #16 w/1 #10 str 4 #16 w/1 #14 or #12 1 #14 Sol w/1 or 2 #12 1 #14 w/1 or 2 #10 1 #14 w/1 #8 Str 2 #14 w/1 #12 or #10 2 #14 w/1 #8 Str or #10 2 #14 w/1 #12 w/ 1 #10 1 #14 w/1 #12 w/1 #10	3 #14 w/1 #10 3 #14 w/1 or 2 #12 1 #12 Sol w/1 #10 Sol 2 #12 w/1 #10 1 #16 w/1 or 2 #14 with 1 #12 1 #16 w/1 to 3 #14 #12 1 #16 w/1 to 2 #10 1 #16 w/1 #12 w/1 #10 2 #16 w/1 #14 w/1 to 2 #12 2 #16 w/1 #12 w/1 #10
Model	600 Volt Maximum			
63 Strip wires 5/8", 7/16" for #18 and smaller	3 to 6 #14 2 to 6 #12 2 to 5 #10 1 to 2 #8 3 #18 w/3 #16 or #14 3 #18 w/1 or 2 #12 or #10 4 #18 w/ 1 or 2 #16 #14 or #12 5 #18 w/ 1 #16 #14 #12 or #10 1 #16 w/ 2 to 5 #14 or #12 1 #16 w/ 1 to 3 #10 2 #16 w/ 1 to 4 #14 or #12 2 #16 w/ 1 or 2 #10 3 #16 w/ 1 to 3 #14 3 #16 w/ 1 or 2 #12 or #10	4 #16 w/ 1 or 2 #14 or #10 4 #16 w/ 1 #10 1 #14 w/ 1 to 4 #12 1 #14 w/ 1 to 3 #10 1 #14 w/ 1 or 2 #8 1 or 2 #14 w/ 1 #16 2 #14 w/ 1 to 4 #12 or #10 2 #14 w/ 1 #18 3 #14 w/ 1 to 3 #12 or #10 3 or 4 #14 w/ 1 #18 3 #14 w/ 1 #16 4 #14 w/ 1 or 2 #12 or #10 4 #14 w/ 1 #16 5 #14 w/ 1 #12 or #10	5 #14 w/ 1 #18 1 #12 w/ 1 or 2 #10 1 #12 w/ 3 #10 1 #12 w/ 1 or 2 #8 1 or 2 #12 w/ 1 or 2 #6 2 #12 w/ 1 or 2 #10 2 #12 w/ 1 #8 or #6 2 #12 w/ 2 #8 3 #12 w/ 1 #10 or #8 3 #12 w/ 2 #10 4 #12 w/ 1 #10 1 #10 w/ 1 or 2 #8 1 #8 w/ 1 #16 1 #16 w/ 1 #14 w/ 1 or 2 #12	2 #16 w/ 1 #14 w/ 1 or 2 #12 2 #16 w/ 2 #14 w/ 1 #12 or #10 2 #16 w/ 1 #12 w/ 1 #10 3 #16 w/ 1 #14 w/ 1 or 2 #12 4 #16 w/ 1 #14 w/ 1 #12 or #10 1 #16 w/ 1 #12 w/ 1 or 2 #10 1 #14 w/ 1 #12 w/ 1 or 2 #10 1 #14 w/ 2 #12 w/ 1 #8 1 #14 w/ 3 #12 w/ 1 #10 1 #14 w/ 1 #10 w/ 1 #8 2 #14 w/ 1 #12 w/ 1 #8 2 #14 w/ 1 #10 w/ 1 #8 3 #14 w/ 1 #10 w/ 1 #8 1 #12 w/ 1 #10 w/ 1 #8
IDEAL UnderGround Wire Connectors				
Model	600 Volt Maximum			
60 Strip wires 1/2"	2 #10 1 to 3 #12 1 to 4 #14 2 #16 or #18 1 #12 w/1 #8 or #10 2 #12 w/1 #10 1 #14 sol w/1 or 2 #12	1 #14 w/1 or 2 #10 1 #14 w/1 #10 w/1 #12 2 #14 w/1 #12 2 #14 w/1 #10 3 #14 w/1 #12 1 #16 w/2 #10 1 #16 w/1 to 3 #12 or #14	1 #16 w/1 #10 or #12 and 1 or 2 #14 2 #16 w/1 or 2 #12 2 #16 w/1 #12 w/1 #14 2 #16 w/1 or 2 #14 2 #16 w/1 #10 3 #16 w/1 or 2 #14	3 #16 w/1 #12 1 #18 w/1 to 3 #12 #14 or #16 2 #18 w/1 or 2 #10 or #12 2 #18 w/1 or 2 #14 or #16 3 #18 w/1 or 2 #16 or #14 3 #18 w/1 #10 1 #20 w/1 to 4 #16 or #18

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL UnderGround Wire Connectors				
Model	600 Volt Maximum			
64® Strip wires 5/8"	3 or 4 #22 solid 3 or 4 #20 solid 2 to 4 # 18 solid 2 to 4 #16 2 to 5 #14 1 to 3 #12 4 #12 sol 1 to 3 #10 1 #20 solid w/ 1 to 4 # 18 or 16 2 #20 solid w/ 1 to 3 # 18 or 16 3 #20 solid w/ 1 or 2 #18 or 16 1 #18 w/ 1 to 4 # 16 14 12	1 #18 w/ 1 to 2 #10 2 #18 w/ 1 to 3 #16 14 12 2 #18 w/ 1 to 2 #10 3 #18 w/ 1 to 2 #16 14 12 3 #18 w/ 1 or 2 #10 1 #16 w/ 1 to 4 #14 12 1 #16 w/ 1 to 2 #10 2 #16 w/ 1 to 4 #14 2 #16 w/ 1 to 3 #12 2 #16 w/ 1 to 2 #10 3 #16 w/ 1 to 3 #14 3 #16 w/ 1 or 2 # 12 10	1 #14 solid w/ 1 or 3 #12 1 #14 w/ 1 or 2 #10 2 #14 w/ 1 to 2 # 12 2 #14 w/ 1 to 2 #10 2 #14 w/ 1 #8 3 #14 w/ 1 # 12 or #10 3 #14 w/ 2 #12 4 #14 w/ 1 #12 or 10 1 #12 w/ 1 or 2 #10 1 #12 w/ 1 #8 2 #12 w/ 1 #10 1 #10 w/ 1 #8	1 #16 w/ 1 or 2 #14 w/ 1 #12 or 10 1 #16 w/ 1 # 12 w/ 1 #10 2 #16 w/ 1 #14 w/ 1 or 2 #12 2 #16 w/ 2 #14 w/ 1 #12 2 #16 w/ 1 #12 w/ 1 #10 3 #16 w/ 1 #14 w/ 1 #12 or 10 1 #14 w/ 1 or 2 #12 w/ 1 #10 2 #14 w/ 1 #12 w/ 1 #10 1 #22 solid w/ 1 #18 w/ 1 #16 1 #22 solid w/ 1 # 20 solid w/ 1 or 2 #16
Model	600 Volt Maximum			
66® Strip wires 1"	1 or 2 #6 2 or 3 #8 2 to 5 #10 3 to 6 #12 1 #6 w/1 or 2 #8 1 #6 w/1 to 3 #10 1 #6 w/1 to 5 #12	1 #6 w/1 to 4 #14 2 #6 w/1 #10 or #12 2 #6 w/1 or 2 #14 1 #8 w/1 to 4 #10 1 #8 w/1 to 5 #12 or #14 2 #8 w/1 or 2 #10	2 #8 w/1 to 3 #12 2 #8 w/1 to 4 #14 3 #8 w/1 or 2 #14 1 #10 w/2 to 4 #12 1 #10 w/3 to 5 #14 2 #10 w/1 to 4 #12 or #14	3 #10 w/1 to 3 #12 or #14 4 #10 w/1 or 2 #12 or #14 1 #12 w/4 or 5 #14 2 #12 w/2 to 4 #14 3 #12 w/1 to 3 #14 4 #12 w/1 #14
IDEAL Twister® AL/CU Wire Connectors				
Model	600 Volt Maximum			
	Copper or Copper only combinations			Copper-or-Aluminum combinations. Not for use on Aluminum-or-Aluminum conductors.
65® Strip wires 1/2" (13mm)	1 to 3 #10 4 #12 sol 1 to 3 #12 1 to 5 #14 1 to 6 #16 2 to 6 #18 3 to 6 #20 4 to 6 #22 2 #22 w/3 to 5 #20 1 #22 w/1 to 5 #18 #16 2 #22 w/1 to 4 #20 #18 #16 3 #22 w/1 to 3 #20 #18 #16 4 #22 w/1 or 2 #20 #18 #16 1 #20 w/1 to 4 #18 #16 #14 2 #20 w/1 to 3 #18 #16 #14 3 #20 w/1 or 2 #18 #16 #14 4 #20 w/1 or 2 #18 #16 #14 1 #18 w/1 to 4 #16 #14 #12 1 #18 w/1 or 2 #10	2 #18 w/1 to 4 #16 #14 #12 2 or 3 #18 w/1 or 2 #10 4 #18 w/1 or 2 #16 #14 #12 4 #18 w/1 #10 5 #18 w/1 #16 or #14 1 #16 w/1 to 4 #14 #12 1 #16 w/1 or 2 #10 2 #16 w/1 to 4 #14 3 #16 w/1 to 3 #14 3 #16 w/1 or 2 #12 #10 4 #16 w/1 or 2 #14 #12 4 #16 w/1 #10 5 #16 w/1 #14 5 #16 sol w/1 #10 sol 1 #14 sol w/1 to 3 #12 1 or 2 #14 w/1 or 2 #10 2 #14 w/1 or 2 #10 2 #14 w/1 #8 3 #14 w/1 #12 or #10	1 #10 AL sol w/1 or 2 #10 CU sol 3 #14 w/2 #12 4 #14 w/1 #12 or #10 1 #12 w/1 or 2 #10 1 #12 w/1 #8 2 #12 w/1 #10 1 #10 w/1 #8 1 #22 w/1 #18 w/1 #16 1 #22 w/1 #20 w/1 or 2 #16 1 #16 w/1 or 2 #14 w/1 #12 or #10 1 #16 w/1 #12 w/1 #10 2 #16 w/1 #14 #w/1 or 2 #12 2 #16 w/2 #14 w/1 #12 2 #16 w/1 #12 w/1 #10 3 #16 w/1 #14 w/1 #12 or #10 4 #16 w/1 #12 w/1 #10 1 #14 w/1 or 2 #12 w/1 #10 2 #14 w/1 #12 w/1 #10	1 #10 AL w/1 or 2 #12 CU 1 #10 AL w/1 or 2 #14 CU 1 #10 AL w/1 or 2 #16 CU 1 #10 AL w/1 or 2 #18 CU 2 #10 AL sol w/1 #12 CU 2 #10 AL sol w/1 #14 CU 2 #10 AL sol w/1 #16 CU 2 #10 AL sol w/1 #18 CU 1 #12 AL sol w/1 or 2 #10 CU 1 #12 AL str w/1 or 2 #10 CU sol 1 #12 AL w/1 or 2 #12 CU 1 #12 AL w/1 or 2 #14 CU 1 #12 AL w/1 or 2 #16 CU 1 #12 AL w/1 or 2 #18 CU 2 #12 AL sol w/1 #10 CU 2 #12 AL sol w/1 #12 CU 2 #12 AL sol w/1 #14 CU 2 #12 AL sol w/1 #16 CU 2 #12 AL sol w/1 #18 CU

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan B-CAP® Wire Connectors				
Model	600 Volt Maximum			
B1 Strip wires 1/2" Strip wires #16 and smaller 5/8"	2 or 3 #12 2 to 4 #14 2 to 5 #16 2 to 6 #18 3 to 6 #20 4 to 6 #22 #20 w/#22 3 or 6* #18 w/#22 3 or 6* #18 w/#20 3 or 6*	#16 w/#22 2 or 6* #16 w/#20 2 or 6* #16 w/#18 2 or 6* #14 w/#22 2 or 4* #14 w/#20 2 or 4* #14 w/#18 2 or 4* #14 w/#16 2 or 4* #12 w/#22 2 or 3* #12 w/#20 2 or 3*	#12 w/#18 2 or 3* #12 w/#16 2 or 3* #12 w/#14 2 or 3* 1 #10 w/1 #12 1 #10 w/1 or 2 #14 1 #10 w/1 or 2 #16 1 #10 w/1 to 3 #18	
Model	600 Volt Maximum			
B2 Strip wires 1/2" Strip wires #16 and smaller 5/8"	2 #10 stranded 2 or 3 #10 solid 2 to 4 #12 stranded 2 to 5 #12 solid 2 to 5 #14 stranded 2 to 6 #14 solid 2 to 5 #16 stranded 2 to 6 #16 solid 2 to 5 #18 stranded 2 to 6 #18 solid 3 to 6 #20	5 or 6 #22 #20 w/#22 4 or 6* #18 w/#22 3 or 6* #18 w/#20 3 or 6* #16 w/#22 3 or 6* #16 w/#20 2 or 6* #16 w/#18 2 or 6* #14 w/#22 2 or 6* #14 w/#20 2 or 6* #14 w/#18 2 or 6* #14 w/#16 2 or 6*	#12 w/#22 2 or 6* #12 w/#20 2 or 6* #12 w/#18 2 or 5* #12 w/#16 2 or 5* #12 w/#14 2 or 5* 1 #10 w/1 to 4 #18 2 #10 w/1 to 3 #18 1 #10 w/1 to 4 #16 2 #10 w/1 to 3 #16 1 #10 w/1 to 4 #14 2 #10 w/1 or 2 #14	1 #10 w/1 to 3 #12 2 #10 w/1 #12 1 #8 stranded w/1 #14 stranded 1 #8 stranded w/1 #12 stranded 1 #8 stranded w/1 #10 stranded 1 #12 w/1 #14 w/1 to 4 #16 1 #12 w/2 #14 w/1 or 2 #16 2 #12 w/1 #14 w/1 to 3 #16
Model	600 Volt Maximum			
B4 Strip wires 3/4"	2 #6 stranded or #8 stranded 2 or 3 #8 solid 2 to 4 #10 stranded 2 to 5 #10 solid 2 to 5 #12	4 to 6 #14 #12 w/#14 2 or 6* #10 w/#14 2 or 5* #10 w/#12 2 or 5* 1 #8 w/1 to 4 #14	1 #8 w/1 to 4 #12 2 #8 w/1 to 3 #12 3 #8 solid w/1 #12 1 #8 w/1 to 4 #10 2 #8 w/1 or 2 #10	1 #6 w/1 to 4 #14 1 #6 w/1 to 4 #12 1 #6 w/1 or 2 #10 1 #6 w/1 or 2 #8
Model	600 Volt Maximum			
BGR/ WGR Strip wires 1"	2 or 3 #10 2 to 5 #12 or #14 2 #10 w/1 or 2 #12 2 #10 w/1 #12 w/1 #14	2 #10 w/1 to 3 #14 1 #10 w/1 to 3 #12 1 #10 w/1 to 4 #14 1 #10 w/1 to 3 #12 w/1 #14	1 #10 w/1 or 2 #12 w/1 or 2 #14 1 #10 w/1 #12 w/1 to 3 #14 4 #12 w/1 #14	3 #12 w/1 or 2 #14 2 #12 w/1 to 3 #14 1 #12 w/1 to 4 #14

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan B-Twist™ Wire Connectors				
Model	600 Volt Maximum			
BT2 Strip wires 1/2"	1 to 4 #10 1 to 5 #12 1 to 6 #14 or #16 2 to 6 #18 3 to 6 #20 4 to 6 #22 1 #8 w/1 to 5 #16 1 #8 w/1 to 4 #14 1 #8 w/1 to 3 #12 1 #8 w 2 #12 w/1 to 4 #14 1 #8 w/1 or 2 #10 1 #8 w/1 #10 w/1 or 2 #14 or #12 1 #8 w/2 #10 w/1 #14 2 #8 1 #10 w/1 to 5 #18, #16 or #14 1 #10 w/1 to 4 #12 1 #10 w/1 #16 w/1 to 4 #18 1 #10 w/1 #14 w/1 to 4 #18 or #16 1 #10 w/2 #14 w/1 to 3 #16 1 #10 w/1 #12 w/1 to 4 #18 or #16 1 #10 w/1 #12 w/1 to 4 #14	1 #10 w/2 #12 w/1 to 3 #18 or #16 1 #10 w/2 #12 w/1 or 2 #14 1 #10 w/3 #12 w/1 #14 1 #10 w/1 to 4 #18 or #16 2 #10 w/1 to 3 #14 2 #10 w/1 to 3 #12 2 #10 w/1 #16 w/1 to 3 #18 2 #10 w/2 #14 w/1 or 2 #16 2 #10 w/1 #12 w/1 to 3 #16 2 #10 w/1 #12 w/1 to 4 #14 2 #10 w/2 #12 w/1 or 2 #18 or #16 2 #10 w/2 #12 w/1 #14 3 #10 w/1 to 3 #18 or #16 3 #10 w/1 or 2 #14 3 #10 w/1 #12 3 #10 w/1 #16 w/1 or 2 #18 3 #10 w/1 #14 w/1 or 2 #18 3 #10 w/1 #14 w/1 #16 3 #10 w/1 #12 w/1 #18 or #16 1 #12 w/1 to 5 #18, #16 or #14 1 or 2 #12 w/1 #16 w/1 to 3 #18	1 or 2 #12 w/1 #14 w/1 to 3 #18 or #16 1 or 2 #12 w/2 #14 w/1 #16 2 #12 w/1 to 4 #18 #16 or #14 3 #12 w/1 to 3 #18 #16 or #14 3 #12 w/1 #16 w/1 or 2 #18 3 #12 w/1 #14 w/1 or 2 #18 or #16 3 #12 w/2 #14 w/1 #16 4 #12 w/1 or 2 #16 4 #12 w/1 #14 4 #12 w/1 #16 w/1 #18 4 #12 w/1 #14 w/1 #18 or #16 1 #14 w/1 to 5 #22 #20 #18 or #16 1 or 2 #14 w/1 #16 w/1 to 3 #18 2 #14 w/1 to 4 #22 #20 #18 or #16 3 #14 w/1 to 3 #22 #20 #18 or #16 3 #14 w/1 #16 w/1 or 2 #18 4 #14 w/1 or 2 #22 #20 #18 or #16 4 #14 w/1 #16 w/1 #18 5 #14 w/1 #18 or #16 1 #16 w/1 to 5 #22 #20 or #18	1 or 2 #16 w/1 or 2 #20 w/1 or 2 #22 or #20 1 #16 w/1 #18 w/1 to 3 #22 or #20 2 #16 w/1 to 3 #22 #20 or #18 3 #16 w/1 to 3 #22 w/1 #20 3 #16 w/1 or 2 #22 w/1 #20 3 #16 w/1 #18 or 2 #22 or #20 4 #16 w/1 or 2 #22 #20 or #18 4 #16 w/1 #22 w/1 #20 4 #16 w/1 #18 w/1 #22 or #20 5 #16 w/1 #22 #20 or #18 1 #18 w/1 to 5 #22 or #20 1 to 3 #18 w/1 or 2 #22 w/1 #20 1 to 3 #18 w/2 #22 or #20 2 #18 w/1 to 4 #22 or #20 3 #18 w/1 to 3 #22 or #20 4 #18 w/1 or 2 #22 or #20 5 #18 w/1 #22 or #20 1 #20 w/3 to 5 #22 2 #20 w/2 to 4 #22 3 #20 w/2 or 3 #22 4 #20 w/2 #22 5 #20 w/1 #22
Buchanan WireTwist™ Wire Connectors				
Model	300 Volt Maximum		600 Volt Maximum	
WT1 Strip solid w res 1/4"; str p stranded w res 5/16"	1 #14 1 or 2 #16 2 or 3 #18 2 to 4 #20 3 or 4 #22 5 #22 solid 1 #14 w/1 #20 or 22 1 #16 w/1 #18 1 #16 w/1 or 2 #20 1 #16 w/1 to 3 #22	1 #18 w/1 to 3 #20 1 #18 w/1 to 4 #22 2 #22 stranded only 4 #20 w/1 #22 3 #20 w/1 or 2 #22 2 #20 w/1 to 3 #22 1 #20 w/1 to 4 #22 1 #16 w/1 #20 w/1 #18 or #20 1 2 #18 w/1 #20 w/1 #22		
Model	300 Volt Maximum		600 Volt Maximum	
WT2 Strip w res 3/8"; str p wires #16 and smaller 1/2"	1 #14 Stranded only 1 #16 Stranded only 2 or 3 #16 1 #18 Stranded only 2 to 4 #18 3 to 5 #20 1 #14 w/1 #16 1 #14 w/1 or 2 #18 1 #14 w/1 to 3 #20 1 #14 w/1 to 4 #22 2 #16 w/1 #18 2 #16 w/1 or 2 #20 2 #16 w/1 to 3 #22	1 #16 w/1 to 3 #18 1 #16 w/1 #18 w/1 #20 1 #16 w/1 to 4 #20 or #22 4 #18 w/1 #20 or #22 3 #18 w/1 or 2 #20 or #22 2 #18 w/1 to 3 #20 or #22 1 #18 w/2 to 4 #20 1 #18 w/3 or 4 #22 4 #20 w/1 #22 3 #20 w/1 or 2 #22 2 #16 w/1 #20 w/1 #22 1 #16 w/1 #22 w/1 #18 or #20 1 or 2 #18 w/1 #20 w/1 #22		
Buchanan WireTwist™ Wire Connectors				
Model	300 Volt Maximum		600 Volt Maximum	
WT3 Strip wires 5/16"; strip wires #16 and	5 #18 5 #22 3 or 4 #16 4 or 5 #20 2 #14 w/2 #16 2 #14 w/1 to 3 #20 or #22	2 #16 w/2 or 3 #18 2 #16 w/3 #22 2 #16 w/3 #20 1 #16 w/4 #18 4 #18 w/1 #20 or #22 3 #18 w/2 #20 or #22	1 or 2 #14 1 #16 Stranded only 2 #16 1 #18 Stranded only 2 to 4 #18 1 #14 w/1 #16	2 #16 w/1 or 2 #22 1 #16 w/1 or 2 #18 1 #16 w/1 to 3 #20 or #22 3 #18 w/1 #20 or #22 2 #18 w/1 or 2 #20 2 #18 w/1 to 3 #22

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

smaller 3/8"	1 #14 w/2 #16 1 #14 w/3 #18 1 #14 w/4 #20 4 #16 w/1 #20 or #22 3 #16 w/1 #18 3 #16 w/1 or 2 #20 or #22	2 #18 w/3 #22 1 #18 str w/5 #22 str 4 #20 w/1 #22 3 #20 w/1 or 2 #22 2 #20 w/2 or 3 #22 1 #20 w/4 #22	1 #14 w/1 #16 and 1 #18 1 #14 w/1 or 2 #18 1 #14 w/1 to 3 #20 1 #14 w/1 to 3 #22 2 #16 w/1 #18 2 #16 w/1 or 2 #20	1 #18 w/2 to 4 #20 1 #18 w/3 or 4 #22 1 or 2 #16 w/1 #20 w/1 #22 1 #16 w/1 #18 w/1 #22 1 or 2 #18 w/1 #20 w/1 #22
Model	300 Volt Maximum		600 Volt Maximum	
WT4 Strip wires 3/8"; str p wires #16 and smaller 7/16"	2 #10 3 #12 5 #16 or #18 1 #10 w/3 or 4 #16 1 #10 w/2 #14 1 #10 w/1 #16 w/4 #20 1 #10 w/1 #16 w/3 or 4 #18 1 #10 w/1 #14 w/4 #22 1 #10 w/1 #14 w/3 #20 1 #10 w/1 #14 w/2 to 4 #18 1 #10 w/1 #14 w/2 #16 1 #10 w/2 #14 w/1 #16 1 #10 w/1 #12 w/1 or 2 #18 1 #10 w/1 #12 w/1 #16 or #14 1 #12 w/3 #14 2 #12 w/1 or 2 #14 2 #12 w/3 #18 1 #14 w/4 #18 or #16 2 #14 w/3 #18 or #16 3 #14 w/2 #18 or #16 3 #14 w/1 #18 w/2 #20 4 #14 w/1 or 2 #16 1 #16 w/4 #18 2 #16 w/3 #18 3 #16 w/2 #18 4 #16 w/1 #18		1 #8 1 #10 1 or 2 #12 1 to 3 #14 2 to 5 #16 2 to 6 #18 3 or 4 #20 4 #22 1 #10 w/1 #14 1 #10 w/1 #12 1 #12 w/1 to 4 #20 #18 or #16 1 #12 w/1 or 2 #14 2 #12 w/1 or 2 #18 2 #12 w/1 #16 1 #14 w/2 to 4 #20 1 #14 w/1 to 3 #18 or #16 2 #14 w/1 to 3 #20 2 #14 w/1 or 2 #18 or #16 3 #14 w/1 or 2 #20 3 #14 w/1 #18 or #16 4 #14 w/1 #20 or #18 1 #16 w/4 #20 1 #16 w/1 to 3 #18 or #20 1 #16 w/2 #22 2 #16 w/1 to 3 #20 2 #16 w/1 or 2 #18 2 #14 w/1 #16 w/1 to 3 #22 3 #16 w/1 or 2 #22 or #20	3 #16 w/1 #18 4 #16 w/1 #22 or #20 1 #18 w/2 #20 1 #18 w/3 #22 2 #18 w/3 #20 3 #18 w/1 or 2 #22 or #20 4 #18 w/1 #22 or #20 2 #12 w/1 #18 w/1 or 2 #20 1 #14 w/1 #16 w/1 to 4 #22 2 #14 w/1 or 2 #20 w/1 or 2 #22 3 #14 w/1 #18 w/1 or 2 #22 3 #14 w/1 #18 w/1 #20 1 #16 w/1 #20 w/4 #22 1 #16 w/1 #18 w/3 or 4 #22 1 #16 w/1 #18 w/2 to 4 #20 2 #16 w/1 or 2 #20 w/1 or 2 #22 3 #16 w/1 #18 w/1 or 2 #22 or #20 1 #18 w/2 #20 w/3 #22 2 #18 w/1 #20 w/3 #22 3 #18 w/1 or 2 #20 w/1 #22 1 #10 w/1 #16 w/1 or 2 #18 1 #10 w/1 #14 w/1 or 2 #20 1 #10 w/1 #14 w/1 #18 1 #12 w/1 #16 w/1 to 4 #20 or #18

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan WireTwist™ Wire Connectors				
Model	300 Volt Maximum		600 Volt Maximum	
WT6 Strip wires 7/16"; strip wires #16 and smaller 1/2"	2 #8 stranded only	2 #10 w/1 #12 w/1 to 3 #18	1 #6 or #8	1 #12 w/2 #14 w/1 to 3 #16
	3 #10	2 #10 w/1 #12 w/1 or 2 #16	1 or 2 #10	2 #12 w/1 or 2 #18 or #16
	5 #12	3 #10 w/1 #18 or #16	1 to 4 #12	1 #8 w/1 or 2 #14
	1 #6 w/1 #14	2 #12 w/2 #14 w/2 #16	2 to 5 #14	2 #12 w/1 to 3 #14
	1 #6 w/1 #12	3 #12 w/2 #14	4 to 6 #16	2 #12 w/1 #16 w/1 to 3 #20
	1 #6 w/1 #14 w/1 or 2 #18	3 #12 w/3 #16	1 #8 w/1 #12	2 #12 w/1 #16 w/1 to 3 #18
	1 #6 w/1 #14 w/1 #16	3 #12 w/1 #16 w/2 #18	1 #10 w/1 to 4 #18 or #16	2 #12 w/1 #14 w/1 to 3 #18
	1 #8 w/4 #16	3 #12 w/1 #14 w/1 or 2 #16	1 #10 w/1 to 3 #14	2 #12 w/1 #14 w/1 to 3 #16
	1 #8 w/3 #14	3 #12 w/1 #14 w/1 or 2 #18	1 #10 w/1 or 2 #12	3 #12 w/1 #14
	1 #8 w/2 #12	3 #12 w/2 #14 w/1 #16	1 #10 w/1 #18 w/1 to 4 #22 or #20	3 #12 w/1 or 2 #16 or #18
	1 #8 w/1 #10	4 #12 w/1 #18 #16 or #14	1 #10 w/1 #16 w/1 to 4 #20	3 #12 w/1 #18 w/1 or 2 #20
	1 #8 w/1 #14 w/4 #18		1 #10 w/1 #16 w/1 to 4 #18	3 #12 w/1 #16 w/1 or 2 #20
	1 #8 w/1 #12 w/1 to 4 #18 or #16		1 #10 w/1 #14 w/1 to 4 #18	2 #12 w/2 #14 w/1 #16 or #18
	1 #8 w/1 #12 w/1 or 2 #14		1 #10 w/1 #14 w/1 to 4 #16 or #18	1 #14 w/3 or 4 #18
	1 #8 w/2 #12 w/1 #16 or #14		1 #10 w/2 #14 w/1 or 2 #16	1 #14 w/1 #16 w/2 to 4 #20
	1 #8 w/1 #10 w/1 #14 or #12		1 #10 w/1 #12 w/1 to 3 #16 or #18	1 or 2 #14 w/1 #16 w/1 to 3 #18
	1 #10 w/4 #14		2 #14 w/1 #18 w/1 to 3 #22 or #20	2 #14 w/2 to 4 #16
	1 #10 w/3 #12		1 #10 w/1 #12 w/1 or 2 #14	2 #14 w/1 #18 w/1 to 3 #22 or #20
	1 #10 w/2 #14 w/3 #16		1 #10 w/2 #12 w/1 #16 or #18	2 #14 w/1 #16 w/1 to 3 #22 or #20
	1 #10 w/1 #12 w/4 #16		2 #10 w/1 to 3 #18	3 #14 w/1 or 2 #18 or #16
	1 #10 w/1 #12 w/3 or 4 #14		2 #10 w/1 or 2 #16	3 #14 w/1 #16 w/1 or 2 #20
	1 #10 w/2 #12 w/2 or 3 #18 or #16		2 #10 w/1 #14	3 #14 w/1 #16 w/1 or 2 #18
	1 #10 w/2 #12 w/1 or 2 #14		2 #10 w/1 #16 w/1 #18	3 #14 w/1 #16 w/1 or 2 #18
	2 #10 w/3 #16		2 #10 w/1 #14 w/1 #20	1 #16 w/4 #18
	2 #10 w/2 or 3 #14		1 #12 w/2 4 #20 or #18	2 #16 w/3 or 4 #18
	2 #10 w/1 or 2 #12		1 #12 w/1 to 4 #16 or #14	2 #16 w/1 #18 w/3 #22
2 #10 w/1 #16 w/2 or 3 #18		1 #12 w/1 #16 w/1 to 4 #20	2 #16 w/1 #18 w/2 or 3 #20	
2 #10 w/1 #14 w/1 to 3 #18		1 #12 w/1 #16 w/1 to 4 #18	3 #16 w/1 or 2 #20 or #18	
2 #10 w/2 #14 w/1 #16		1 #12 w/1 #14 w/1 to 4 #20 #18 or #16	4 #16 w/1 #20 or #18	
Buchanan WingTwist™ Wire Connectors				
Model	600 Volt Maximum			
WT51 Strip wires 3/8"	1 #10	3 #16 w/1 to 3 #18	3 #14 w/1 or 2 #18	2 #12 w/1 or 2 #18
	1 to 3 #12 or #14	4 #16 w/1 or 2 #18	3 #14 w/1 #16 or #18	2 #12 w/1 #16 or #14
	2 to 4 #16 or #18	1 #14 w/1 to 5 #18	1 #12 w/1 to 5 #18	1 #10 w/1 to 3 #18
	1 #16 w/1 to 5 #18	1 #14 w/1 to 4 #16	1 #12 w/1 to 3 #16	1 #10 w/1 or 2 #16 or #14
	2 #16 w/1 to 4 #18	2 #14 w/1 to 3 #18 or #16	1 #12 w/1 or 2 #14	1 #10 w/1 #12

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan WingTwist™ Wire Connectors					
Model	600 Volt Maximum				
WT41 Strip wires 1/2"	1 to 3 #10	4 #20 w/1 or 2 #18 #16 or #14	2 #16 w/1 to 3 #12 or #14	1 #12 w/1 #8	
	4 #12 solid	1 #16 stranded	3 #16 w/1 or 2 #12 or #10	2 #12 w/1 #10	
	1 to 3 #12	1 #18 w/1 to 4 #16 #14 or #12	4 #16 w/1 or 2 #14 or #12	1 #10 w/1 #8	
	1 to 5 #14	1 #18 w/1 or 2 #10	4 #16 w/ 1 #10	1 #22 w/1 #18 w/1 #16	
	2 to 6 #20 #18 or #16	2 #18 w/1 to 4 #16 or #14	5 #16 w/1 #14	1 #22 w/1 #20 w/1 or 2 #16	
	3 to 6 #22	2 #18 w/1 to 3 #12	5 #16 solid w/1 #10 solid	1 #16 w/ 1 or 2 #14 w/1 #12 or #10	
	1 #22 solid w/1 #20 solid	2 #18 w/1 or 2 #10	1 #14 solid w/1 to 3 #12	1 #16 w/1 #12 w/1 #10	
	1 #22 w/2 to 5 #20	3 #18 w/1 to 3 #16 #14 or #12	1 #14 w/1 or 2 #10	2 #16 w/1 #14 w/1 or 2 #12	
	1 #22 w/1 to 5 #18 #16	3 #18 w/1 or 2 #10	2 #14 w/1 or 2 #12	2 #16 w/2 #14 w/1 #12	
	2 #22 w/1 to 4 #20 #18 or #16	4 #18 w/1 or 2 #16 #14 or #12	2 #14 w/ 1 or 2 #12	2 #16 w/1 #12 w/1 #10	
	3 #22 w/1 to 3 #20 #18 or #16	4 #18 w/1 #10	2 #14 w/ 1 #8	3 #16 w/1 #14 w/1 #12 or #10	
	4 #22 w/1 or 2 #2 #18 or #16	5 #18 w/1 #16 or #14	3 #14 w/1 #12 or #10	4 #16 w/1 #12 w/1 #10	
	1 #20 w/1 to 4 #18 #16 or #14	1 #16 w/1 to 4 #14 or #12	3 #14 w/2 #12	1 #14 w/1 or 2 #12 w/1 #10	
	2 #20 w/1 to 3 #18 #16 or #14	1 #16 w/1 or 2 #10	4 #14 w/1 #12 or #10	2 #14 w/1 #12 w/1 #10	
3 #20 w/1 or 2 #18 #16 or #14	2 #16 w/1 to 4 #14	1 #12 w/1 or 2 #10			
Model	600 Volt Maximum				
WT52 Strip wires 1/2"	2 to 3 #10	1 #10 w/1 #12	1 #12 w/1 to 5 #16	1 #14 w/2 to 5 #16	
	2 to 5 #12	1 #8 w/1 #10 #12 or #14	1 #12 w/1 to 4 #14	2 #14 w/1 to 4 #18 or #16	
	2 to 6 #14	1 #10 w/2 to 5 #18	1 #12 w/1 #14 and 1 to 4 #16	3 #14 w/1 to 3 #16	
	4 to 6 #16	1 #10 w/1 to 4 #16	1 #12 w/2 #14 and 1 or 2 #16	4 #14 w/1 or 2 #18	
	6 #18	1 #10 w/1 or 2 #14 or #12	2 #12 w/3 or 4 #18	4 #14 w/1 #16	
	1 #12 w/5 #14	1 #10 w/1 #14 and 1 to 3 #16	2 #12 w/1 to 3 #16	5 #14 w/1 #18	
	1 #12 w/4 #16 or #14	1 #10 w/2 #14 and 1 #16	2 #12 w/1 to 3 #14	1 #16 w/4 or 5 #18	
	1 #12 w/2 #14	1 #10 w/1 #12 and 1 #14	2 #12 w/1 #14 and 1 or 2 #16	2 #16 w/2 to 4 #18	
	1 #12 w/1 #14	1 #10 w/1 #12 and 1 or 2 #16	3 #12 w/1 or 2 #16	3 #16 w/1 to 3 #18	
	1 #10 w/3 #14	2 #10 w/1 or 2 #16	3 #12 w/2 #18	4 #16 w/1 or 2 #18	
	1 #10 w/4 #14	2 #10 w/1 #14	1 #14 w/3 to 5 #18	5 #16 w/1 #18	
	1 #10 w/2 #14	1 #12 w/2 to 5 #18	1 #14 w/3 #12		
	Model	600 Volt Maximum			
	WT53 Strip wires 1/2"	1 #6	1 #12 w/3 to 5 #16	3 #10 w/1 #14 or #12	1 #10 w/1 #12 w/1 to 4 #14
2 #8		1 #12 w/2 to 5 #14	1 #8 w/1 to 5 #14	1 #10 w/2 #12 w/1 to 3 #14	
2 or 3 #10		2 #12 w/3 or 4 #18	1 #8 w/1 to 3 #12	1 #10 w/3 #12 w/1 #14	
2 to 6 #12		2 #12 w/1 to 4 #16 or #14	1 #8 w/1 or 2 #10	2 #10 w/2 #12 w/1 or 2 #14	
4 to 6 #14		3 #12 w/1 to 3 #18 or #16	2 #8 w/1 #14	1 #8 w/1 #12 w/1 to 3 #14	
4 #16 w/2 #18		3 #12 w/1 to 3 #14	1 #6 w/1 #10	1 #8 w/2 #12 w/1 #14	
1 #14 w/4 or 5 #16		4 #12 w/1 or 2 #16	1 #12 w/1 #14 w/1 to 4 #16	1 #8 w/1 #10 w/1 or 2 #14	
2 #14 w/3 or 4 #18		1 #10 w/1 to 5 #16 or #14	1 #12 w/2 #14 w/1 #16	1 #8 w/1 #10 w/1 #12	
2 #14 w/2 to 4 #16		1 #10 w/1 to 4 #12	2 #12 w/1 #14 w/1 or 2 #16		
3 #14 w/1 to 3 #18 or #16		2 #10 w/2 to 4 #18 or #16	1 #10 w/1 #14 w/1 to 3 #16		
4 #14 w/1 or 2 #18 or #16		2 #10 w/1 to 4 #14	1 #10 w/2 #14 w/1 #16		
5 #14 w/1 #18 or #16		2 #10 w/1 or 2 #12	1 #10 w/1 #12 w/1 or 2 #6		

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan WingTwist™ Wire Connectors				
Model	600 Volt Maximum			
WT54 Strip wires 5/8"	1 or 2 #6 2 or 3 #8 2 to 5 #10 3 to 6 #12 5 or 6 #14 1 #12 w/4 or 5 #14 2 #12 w/2 to 4 #14 3 #12 w/1 to 3 #14 4 #12 w/1 #14 1 #10 w/3 to 5 #14 1 #10 w/2 to 4 #14 2 #10 w/1 to 4 #14 or #12 3 #10 w/1 to 3 #14 or #12 4 #10 w/1 or 2 #14 or #12 1 #8 w/1 to 5 #14 or #12 1 #8 w/1 to 4 #10	2 #8 w/1 to 4 #14 2 #8 w/1 to 3 #12 2 #8 w/1 or 2 #10 3 #8 w/1 or 2 #14 1 #6 w/1 to 4 #14 1 #6 w/1 to 5 #12 1 #6 w/1 to 3 #10 1 #6 w/1 or 2 #8 2 #6 w/1 #14 2 #6 w/1 #12 1 #10 w/1 #12 w/1 to 4 #14 1 #10 w/2 #12 w/1 to 3 #14 1 #10 w/3 #12 w/1 or 2 #14 1 #10 w/4 #12 w/1 #14 2 #10 w/1 #12 w/1 to 3 #14 2 #10 w/2 #12 w/1 or 2 #14	2 #10 w/3 #12 w/1 #14 3 #10 w/1 #12 w/1 or 2 #14 3 #10 w/2 #12 w/1 #14 4 #10 w/1 #12 w/1 #14 1 #8 w/1 #12 w/1 to 4 #14 1 #8 w/2 #12 w/1 to 3 #14 1 #8 w/3 #12 w/1 or 2 #14 1 #8 w/4 #12 w/1 #14 1 #8 w/1 #10 w/1 to 4 #14 1 #8 w/1 #10 w/1 to 4 #12 1 #8 w/2 #10 w/1 to 3 #14 1 #8 w/2 #10 w/1 to 3 #12 1 #8 w/3 #10 w/1 or 2 #14 1 #8 w/3 #10 w/1 #12 2 #8 w/1 #12 w/1 to 3 #14 2 #8 w/2 #12 w/1 or 2 #14	2 #8 w/3 #12 w/1 #14 2 #8 w/1 #10 w/1 to 3 #14 2 #8 w/1 #10 w/1 or 2 #12 2 #8 w/2 #10 w/1 #14 Sol 1 #6 w/1 #12 w/1 to 4 #14 1 #6 w/2 #12 w/1 to 3 #14 1 #6 w/3 #12 w/1 or 2 #14 1 #6 w/4 #12 w/1 #14 1 #6 w/1 #10 w/1 to 4 #14 1 #6 w/1 #10 w/1 to 3 #12 1 #6 w/2 #10 w/1 or 2 #14 1 #6 w/2 #10 w/1 #12 1 #6 w/1 #8 w/1 to 3 #14 1 #6 w/1 #8 w/1 or 2 #12 1 #6 w/1 #8 w/1 #10
IDEAL Set Screw Wire Connectors				
Model	300 Volt Maximum			
10	1 #10 or #12 1 or 2 #14 2 to 4 #16 2 to 6 #18 or #20 4 to 6 #22 1 #10 str w/1 #20 1 #10 str w/1 or 2 #22 1 #12 str w/1 #14 1 #12 str w/1 #16 w/1 #18 1 #12 str w/1 or 2 #18 or #20 1 #12 str w/1 #18 or #20 w/1 or 2 #22 1 #12 w/3 or 4 #20 or #22 2 #14 w/1 #16 1 #14 w/1 or 2 #16	2 #14 str w/1 #16 w/1 #20 or #22 1 #14 str w/1 #16 w/1 #18 #20 or #22 2 #14 w/1 or 2 #18 1 #14 w/1 to 3 #18 2 #14 str w/1 #18 or #20 w/1 or 2 #22 1 #14 str w/1 #18 or #20 w/1 or 2 #22 2 #14 w/1 to 3 #20 1 #14 w/3 to 5 #20 1 #14 str w/1 or 2 #20 1 #14 str w/2 to 5 #22 2 #14 w/3 or 4 #22	2 #14 str w/1 or 2 #22 1 #16 w/1 to 5 #20 or #22 1 #16 w/1 to 4 #18 1 #16 w/1 #20 w/1 or 2 #22 1 #16 w/1 #18 w/1 or 2 #22 2 #16 w/1 to 4 #20 or #22 2 #16 w/1 to 3 #18 3 #16 w/1 #18 or #20 w/1 or 2 #22 3 #16 w/1 to 3 #20 or #22 4 #16 w/1 #18 #20 or #22 4 #16 w/1 #20 w/1 #22 1 #18 w/1 to 5 #20 or #22 1 #18 w/1 #20 w/1 or 2 #22 2 #18 w/1 to 4 #20 or #22	2 #18 w/1 #20 w/1 or 2 #22 3 #18 w/1 to 4 #22 3 #18 w/1 to 3 #20 3 #18 w/1 #20 w/1 or 2 #22 4 #18 w/1 or 2 #20 or #22 4 #18 w/1 #20 w/1 or 2 #22 5 #18 w/1 #20 w/1 or 2 #22 1 #20 w/1 to 5 #22 2 #20 w/1 to 4 #22 3 #20 w/1 to 3 #22 4 #20 w/1 or 2 #22 5 #20 w/1 #22 3 #16 w/1 or 2 #18
Model	600 Volt Maximum			
11	1 #10 2 #12 2 or 3 #14 4 or 5 #16 1 #10 str w/1 or 2 #16 #18 or #20 1 #10 w/3 or 4 #18 1 #10 w/3 #16 1 #12 w/4 #18 1 #12 w/2 #14 1 #12 w/1 #16 1 #12 w/3 to 5 #20 1 #12 w/1 to 3 #16 or #18 1 #12 w/1 #14 2 #12 w/2 or 3 #20	2 #12 w/1 or 2 #18 3 #14 w/5 #22 3 #14 w/3 #20 1 #14 w/2 to 5 #22 1 #14 w/1 to 5 #18 or #20 1 #14 w/1 to 4 #16 2 #14 w/1 to 5 #20 or #22 2 #14 w/1 to 4 #18 2 #14 w/1 to 3 #16 3 #14 w/1 to 3 #22 3 #14 w/1 or 2 #18 or #20 3 #14 w/1 #16 1 #16 w/4 or 5 #22 1 #16 w/3 to 5 #20 1 #16 w/2 to 5 #18	2 #16 w/1 to 5 #22 2 #16 w/2 to 5 #20 2 #16 w/1 to 4 #18 3 #16 w/1 to 5 #22 3 #16 w/1 to 4 #20 3 #16 w/1 to 3 #18 4 #16 w/1 to 5 #22 4 #16 w/1 or 2 #18 or #20 5 #16 w/1 to 4 #22 5 #16 w/1 #18 or 1 #20 6 or 7 #18 1 #18 w/4 or 5 #20 or #22 2 #18 w/2 to 5 #22 2 #18 w/3 or 4 #20 3 #18 w/1 to 5 #22	3 #18 w/1 to 3 #20 4 #18 w/1 to 5 #22 4 #18 w/1 or 2 #20 5 #18 w/1 to 5 #22 5 #18 w/1 #20 1 #20 w/4 or 5 #22 2 or 4 #20 w/3 to 5 #22 5 #20 w/1 to 5 #22

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Set Screw Wire Connectors				
Model	600 Volt Maximum			
22	1 or 2 #10 2 to 4 #12 2 to 6 #14 4 to 6 #16 2 to 6 #18 1 #10 str w/3 to 5 #20 1 #10 w/3 to 5 #18 1 #10 w/2 to 5 #16 1 #10 w/1 to 4 #14 1 #10 w/1 or 2 #12	2 #10 w/2 to 4 #20 2 #10 w/1 to 3 #18 2 #10 w/1 or 2 #16 2 #10 w/1 #14 2 #10 w/1 #12 1 #12 w/3 to 5 #18 1 #12 w/2 to 5 #16 1 #12 w/1 to 5 #14 2 #12 w/1 to 4 #18 2 #12 w/1 to 4 #16	2 #12 w/1 to 4 #14 3 #12 w/1 to 3 #18 3 #12 w/1 or 2 #16 3 #12 w/1 #14 1 #14 w/3 to 5 #18 1 #14 w/2 to 5 #16 2 #14 w/2 to 4 #20 2 #14 w/1 to 4 #16 3 #14 w/2 or 3 #20 3 #14 w/1 to 3 #16	4 #14 w/1 or 2 #16 5 #14 w/1 #16 1 #16 w/3 to 5 #18 2 #16 w/2 to 4 #18 3 #16 str w/1 or 3 #18 str 4 #16 w/1 or 2 #18 5 #16 w/1 #18
IDEAL Crimp Connectors				
Model	600 Volt Maximum			
48 Crimp	1 to 3 #16 1 to 4 #18 1 to 5 #20 1 to 6 #22 1 #14 w/1 to 3 #22 1 #14 w/1 to 3 #20 1 #14 w/1 or 2 #18 1 #14 w/1 #16 1 #14 w/1 #18 w/1 to 3 #22 1 #14 w/1 #18 w/1 or 2 #20 1 #14 w/1 #18 w/1 #20 w/1 #22	1 #16 w/1 to 5 #22 1 #16 w/1 to 4 #20 1 #16 w/1 to 3 #18 1 #16 w/2 #22 1 #16 w/1 #18 w/1 #22 1 #16 w/2 #18 w/1 #20 1 #16 w/2 #18 w/1 or 2 #22 1 #16 w/1 #18 w/1 #20 w/1 #22 1 #16 w/1 #18 w/1 or 2 #20 w/1 #22 2 #16 w/1 to 3 #22	2 #16 w/1 or 2 #20 2 #16 w/1 #18 w/1 #22 2 #16 w/1 #20 w/1 #22 2 #16 w/1 #18 1 #18 w/1 to 5 #20 or #22 2 #18 w/1 to 3 #20 3 #18 w/1 to 3 #22 3 #18 w/1 or 2 #20 1 #18 w/1 to 4 #20 w/1 #22 1 #18 w/1 #20 w/2 to 4 #22 1 #18 w/2 #20 w/2 or 3 #22 1 #18 w/3 #20 w/2 #22	2 #18 w/1 or 2 #20 w/1 #22 2 #18 w/1 #20 w/1 to 3 #22 3 #18 w/1 #20 w/1 #22 2 #20 w/1 to 4 #22 3 #20 w/1 to 3 #22 4 #20 w/1 or 2 #22 5 #20 w/1 #22 1 #20 w/1 to 4 #22
Model	600 Volt Maximum			
49 Crimp	1 or 2 #14 1 to 4 #16 1 to 6 #18 1 to 6 #20 1 #12 str w/1 or 2 #18 1 #12 str w/1 #16 1 #14 w/1 to 3 #18 #14 w/1 to 3 #16	1 #14 w/2 or 3 #20 1 #14 w/1 #17 w/ 1 #20 1 #16 w/1 to 4 #18 1 #16 w/1 to 4 #20 1 #16 w/1 #18 w/1 #20 2 #16 w/1 or 2 #18 2 #16 w/2 or 3 #20 3 #16 w/1 #18 w/ 1 #20	1 #17 w/1 #18 w/1 #20 all str 1 #17 w/1 #18 w/1 #20 w/ 1 #22 all str 1 #18 w/1 #22 1 #18 w/2 to 4 #20 1 or 2 #18 w/1 #20 2 #18 w/1 or 4 #20 2 #18 w/1 #22	3 #18 w/1 #22 4 #18 w/1 #22 1 #22 1 #20 w/1 #22 2 or 3 #22 1 #17 w/1 #18 w/1 #20 w/2 #22
Model	600 Volt Maximum			
NC-8 Stranded Wire Only	2 #10 2 or 3 #12 3 to 5 #14 4 to 7 #16 7 to 12 #18 1 #8 w/1 #14 #16 or #18 1 #8 w/2 #18 1 #10 w/1 #12	1 #10 w/2 #14 1 #10 w/1 2 to 4 #16 (no 3 #16's) 1 #10 w/1 to 6 #18 1 #12 w/2 to 8 #18 1 #12 w/2 to 5 #16 1 #12 w/2 or 3 #14 2 #12 w/1 to 4 #14	2 #12 w/1 to 3 #16 2 #12 w/2 #14 1 #14 w/4 to 10 #18 1 #14 w/3 to 6 #16 2 #14 w/2 to 7 #18 2 #14 w/1 to 4 #16 3 #14 w/1 to 5 #18 3 #14 w/1 to 3 #16	4 #14 w/1 or 2 #18 1 #16 w/5 to 11 #18 2 #16 w/4 to 9 #18 3 #16 w/2 to 7 #18 4 #16 w/1 to 6 #18 5 #16 w/1 to 4 #18 6 #16 w/1 #18

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

IDEAL Crimp Connectors				
Model	600 Volt Maximum			
410	2 #10 str	1 #10 w/2 #12	1 #16 w/3 to 7 #18	2 #12 w/1 #18 w/4 #16
	2 to 4 #12	1 #10 str or sol w/1 or 2 or 4 or 7 #18	2 #16 w/2 to 8 #18	2 #12 w/1 to 3 #18 w/3 #16
	3 to 6 #14	(no combinations with 3 #18)	3 #16 w/1 to 7 #18	2 #12 w/1 to 4 #18 w/2 #16
	2 #14 str	1 #10 str or sol w/1 to 6 #16 str	4 #16 w/1 to 5 #18	2 #12 w/1 to 5 #18 w/1 #16
	3 to 7 #16	1 #10 str w/1 to 6 #16 sol	5 #16 w/1 to 4 #18	3 #12 w/1 or 2 #18 w/1 #16
	5 to 10 #18	1 #12 w/1 to 9 #18 or 1 to 7 #16	6 #16 w/1 or 2 #18	1 #14 w/1 #18 w/6 #16
	1 #14 sol w/1 #14 str	2 #12 w/1 to 6 #18 or 1 to 4 #16	7 #16 w/1 #18	1 #14 w/1 or 2 #18 w/5 #16
	1 #10 sol w/1 #10 str	3 #12 w/1 to 3 #18 or #1 or 2 #16	1 #10 w/1 #18 w/5 #16	1 #14 w/1 to 4 #18 w/4 #16
	1 #14 w/1 to 3 #12	1 #14 w/1 to 9 #18	1 #10 w/1 to 3 #18 w/4 #16	1 #14 w/1 to 5 #18 w/3 #16
	1 #14 w/1 or 2 #12 w/1 #10	1 #14 w/1 to 7 #16	1 #10 w/1 to 4 #18 w/3 #16	1 #14 w/1 to 7 #18 w/2 #16
	2 #14 w/1 or 2 #12	2 #14 w/1 to 8 #18 or 1 to 5 #16	1 #10 w/1 to 6 #18 w/2 #16	1 #14 w/1 to 8 #18 w/1 #16
	2 #14 w/1 #10 w/1 #12	3 #14 w/1 to 5 #18	1 #10 w/1 to 8 #18 w/1 #16	2 #14 w/1 #18 w/4 #16
	3 #14 w/1 or 2 #12	3 #14 w/1 to 4 #16	2 #10 w/1 or 2 #16	2 #14 w/3 #18 w/3 #16
	3 #14 w/1 #10	4 #14 w/1 to 3 #18 or 1 or 2 #16	2 #10 w/1 or 2 #18 w/1 #16	2 #14 w/5 #18 w/2 #16
	1 #12 w/1 to 4 #14		2 #10 w/1 to 4 #18	2 #14 w/7 #18 w/1 #16
	2 #12 w/1 to 3 #14		1 #12 w/1 or 2 #18 w/6 #16	3 #14 w/1 or 2 #18 w/3 #16
	2 #12 w/1 #10		1 #12 w/1 to 3 #18 w/5 #16	3 #14 w/1 to 4 #18 w/2 #16
2 #10 w/1 or 2 #14		1 #12 w/1 to 4 #18 w/4 #16	3 #14 w/1 to 5 #18 w/1 #16	
2 #10 w/1 #12		1 #12 w/1 to 5 #18 w/3 #16	4 #14 w/1 to 2 #18 w/1 #16	
1 #10 w/1 to 4 #14		1 #12 w/1 to 6 #18 w/2 #16		
1 #10 w/1 #12		1 #12 w/1 to 8 #18 w/1 #16		
Model	600 Volt Maximum			
411	2 #8	2 #8 w/1 or 2 #14	2 #10 w/1 or 3 #12 #14 or #16	3 #12 w/1 or 2 #14 #16 or #18
	2 or 3 #10	1 #8 w/1 or 2 #10	2 #10 w/1 or 3 #18	2 #12 w/2 or 3 #14
	4 #10 sol	1 #8 w/1 or 3 #12	1 #10 w/2 or 4 #12	2 #12 w/3 #16
	3 or 5 #12	1 #8 w/1 or 4 #14	1 #10 w/3 or 4 #14	1 #12 w/4 #14
	5 #14	3 #10 w/1 #12	1 #10 w/4 #16	1 #8 w/4 #18
	2 #8 w/1 #12	3 #10 w/1 or 2 #14 #16 or #18	4 #12 w/1 #14 #16 or #18	
Model	600 Volt Maximum			
412	2 #6	1 #6 w/1 or 2 #8	2 #10 w/1 to 5 #12	1 #14 w/1 to 6 #16
	2 or 3 #8	1 #6 w/4 #16	3 #10 w/1 to 4 #18 #16 or #14	2 #14 w/1 to 5 #18 or #16
	2 to 5 #10	2 #6 w/1 #14 or #12	3 #10 w/1 to 3 #12	3 #14 w/2 to 4 #18
	2 to 6 #12	1 #8 w/1 to 5 #14 or #12	4 #10 w/1 to 3 #18 #16 or #14	3 #14 w/1 to 3 #16
	2 to 7 #14	1 #8 w/1 to 3 #10	4 #10 w/1 or 2 #12	4 #14 w/1 to 3 #18 or #16
	3 to 7 #16	1 #8 w/2 or 3 #16	1 #12 w/1 to 6 #18 #16 or #14	5 #14 w/1 or 2 #18 or #16
	5 to 7 #18	1 #8 w/4 #18	2 #12 w/1 to 5 #18 or #16	6 #14 w/1 #18 or #16
	1 #4 w/1 to 3 #14	2 #8 w/1 to 5 #14	2 #12 w/1 to 5 #14	1 #16 w/4 to 6 #18
	1 #4 w/1 or 2 #12	2 #8 w/1 to 3 #12	3 #12 w/1 to 3 #18	2 #16 w/2 to 5 #18
	1 #4 w/1 #10	2 #8 w/1 or 2 #10	3 #12 w/1 to 3 #16	3 #16 w/1 to 4 #18
	1 #4 w/1 #8	1 #10 w/1 to 6 #18	3 #12 w/1 to 4 #14	4 #16 w/1 to 3 #18
	1 #6 w/1 to 6 #14	1 #10 w/1 to 6 #16	4 #12 w/1 to 3 #18 #16 or #14	5 #16 w/1 or 2 #18
	1 #6 w/1 to 5 #12	1 #10 w/1 to 5 #14 or #12	5 #12 w/1 or 2 #18 #16 or #14	6 #16 w/1 #18
	1 #6 w/1 to 3 #10	2 #10 w/1 to 5 #18 #16 or #14	1 #14 w/2 to 6 #18	

UNDERWRITER'S LABORATORIES LISTED WIRE COMBINATIONS

Combinations listed on this page are CU/CU Wire only. (Do not use on aluminum wire.) For use on solid and/or stranded wire combinations unless noted otherwise.

Buchanan Crimp Connectors				
Model	600 Volt Maximum			
2006S	2 #18 Stranded through 10 #18 Solid or Stranded #18 w/1 to 6 #16 or 1 to 5 #15 or 1 to 3 #12 or 1 #10 2 #18 stranded w/1 to 5 #16 or 1 to 5 #14 or 1 to 3 #12 or 1 #10 3 #18 w/1 to 5 #16 or 1 to 4 #14 or 1 or 2 #12 4 #18 w/1 to 4 #16 or 1 to 3 #14 or 1 or 2 #12 or 1 #10 5 #18 w/1 to 3 #16 or 1 or 2 #14 or 1 #12 or 1 #10 6 #18 w/1 to 3 #16 or 1 or 2 #14 or 1 #12 7 #18 w/1 or 2 #16 or 1 #14	8 #18 w/1 #16 2 to 7 # 16 1 #16 w/1 to 4 #14 or 1 to 3 #12 or 1 #10 2 #16 w/1 to 3 #14 or 1 or 2 #12 or 1 #10 3 #16 w/1 or 2 #14 or 1 #12 or 1 #10 4 #16 w/1 #14 or 1 #12 2 to 5 #14 1 #14 w/1 to 3 #12 or 1 #10 2 #14 w/1 or 2 # 12 or 1 #10 3 #14 w/1 #12 2 to 4 #12 1 #12 w/1 #10 2 # 10	1 #14 w/1 #12 and 1 #10 2 #14 w/1 #12 and 1 #10 1 #10 w/5 #16 and 1 #18 1 #10 w/4 #16 and 1 to 3 #18 2 #10 w/1 #16 and 1# 18 1 #12 w/5 #16 and 1 to 3 #18 1 #12 w/4 #16 and 1 to 4 #18 1 #12 w/3 #16 and 1 to 5 #18 1 #12 w/2 #16 and 1 to 6 #18 1 #12 w/1 #16 and 1 to 8 #18 2 #12 w/4 #16 and 1 #18 2 #12 w/2 #16 and 1 to 4 #18 2 #12 w/1 #16 and 1 to 5 #18 3 #12 w/1 #16 and 1 or 2 #18 1 #14 w/6 #16 and 1 #18 1 #14 w/5 #16 and 1 or 2 #18	1 #14 w/4 #16 and 1 to 4 #18 1 #14 w/3 #16 and 1 to 5 #18 1 #14 w/2 #16 and 1 to 7 #18 1 #14 w/2 #16 and 1 to 8 #18 2 #14 w/4 #16 and 1 #18 2 #14 w/3 #16 and 3 #18 2 #14 w/2 #16 and 5 #18 2 #14 w/1 #16 and 7 #18 3 #14 w/3 #16 and 1 or 2 #18 3 #14 w/2 #16 and 1 to 4 #18 3 #14 w/1 #16 and 1 to 5 #18 4 #14 w/1 #16 and 1 or 2 #18
Model	600 Volt Maximum			
2011S	Solid Wire 4 to 10 # 14 3 to 6 #12 2 to 4 #10 2 #8	Stranded Wire 5 to 11 # 14 3 to 7 #12 2 to 5 #10 2 or 3 #8 2 #6	Combination Stranded Wire 1 to 3 #14 w/3 to 5 #12 1 to 3 #14 w/3 or 4 #10 1 or 2 #12 w/3 or 4 #10 1 to 3 #12 w/5 to 8 #14 2 or 4 # 14 w/1 #8 or 1 #10 1 #8 w/1 #10 1 #4 w/1 #8 or 1 #10	Combination Stranded & Solid 1 to 3 #14 w/3 to 5 #12 1 to 3 #14 w/3 or 4 #10 1 or 2 #12 w/3 or 4 #10 1 to 3 #12 w/5 to 8 #14 1 #4 stranded w/1 #8 or 1 #10 1 #6 stranded w/1 #8 or 1 #10 1 #8 w/1 #10 2 or 4 #14 solid w/1 #8 str
Model	600 Volt Maximum			
2008S	2 to 10 #18 1 #18 w/1 to 6 #16 or 1 to 5 #14 or 1 to 3 #12 or 1 #10 2 #18 w/1 to 5 #16 or 1 to 5 #14 or 1 to 3 #12 or 1 #10 2 #16 w/1 to 3 #14 or 1 or 2 #12 or 1 #10 3 #16 w/1 or 2 #14 or 1 #12 or 1 #10 4 #16 w/1 #14 or 1 #12 2 to 5 #14	1 #14 w/1 to 3 #12 or 1 #10 2 #14 w/1 or 2 #12 or 1 #10 3 #14 w/1 #12 2 to 4 #12 1 #12 w/1 #10 2 #10 1 #14 w/1 #12 and 1 #10 2 #14 w/1 #12 and 1 #10 1 #10 w/5 #16 and 1 #18 1 #10 w/4 #16 and 1 to 3 #18 2 #10 w/1 #16 and 1 #18	1 #12 w/5 #16 and 1 to 3 #18 1 #12 w/4 #16 and 1 to 4 #18 1 #12 w/3 #16 and 1 to 5 #18 1 #12 w/2 #16 and 1 to 6 #18 2 #12 w/1 #16 and 1 or 2 #18 1 #14 w/6 #16 and 1 #18 1 #14 w/5 #16 and 1 or 2 #18 1 #14 w/4 #16 and 1 to 4 #18 1 #14 w/3 #16 and 1 to 5 #18 1 #14 w/2 #16 and 1 to 7 #18 1 #14 w/1 #16 and 1 to 8 #18	2 #14 w/4 #16 and 1 #18 2 #14 w/3 #16 and 3 #18 2 #14 w/2 #16 and 5 #18 2 #14 w/1 #16 and 7 #18 3 #14 w/3 #16 and 1 or 2 #18 3 #14 w/2 #16 and 1 to 4 #18 3 #14 w/1 #16 and 1 to 5 #18 4 #14 w/1 #16 and 1 or 2 #18
Term-End Lugs				
Model	Solid Wire		Stranded Wire	
16-8	1 or 8 #16 1 or 4 #14	1 or 2 #12 1 #10	1 or 8 #16 1 or 5 #14	1 or 3 #12 1 #8
IDEAL Term-A-Nut™ Pigtail Connectors and Grounding Connectors				
70 Red w/blk or wh te Green w/grn	2 or 4 #12 or #14 4 or 5 # 16 1 #16 w/3 or 4 #18 2 #16 w/2 or 3 #18 3 #16 w/1 or 2 #18 4 #16 w/1 #18 1 #14 w/ 2 3 #18	2 #14 w/1 or 2 #18 3 #14 w/1 #18 1 #14 w/2 or 3 #16 2 #14 w/1 or 2 #16 3 #14 w/1 #16 1 #12 w/2 or 3 #18 2 #12 w/1 or 2 #18	3 #12 w/1 #18 1 #12 w/1 or 3 #16 2 #12 w/1 or 2 #16 3 #12 w/1 #16 1 #12 w/1 or 3 #14 2 #12 w/1 or 2 #14 3 #12 w/ 1 #14	