



# 600A AC/DC Auto-Ranging Digital Pro Clamp Meter



Klein Tools CL710 Clamp Meter delivers accurate measurements across AC/DC current, voltage, resistance, continuity, frequency, and capacitance, all with True RMS precision. It features diode testing and a Low Impedance (LoZ) mode to eliminate ghost voltages. The clamp features NCV detection with escalating audio-visual alerts the closer to the voltage source. The transfective reverse-contrast display and lighted dial ensure visibility in any lighting; a reliable tool for diverse applications.

## Specifications

<b>Type:</b>	Pro Clamp Meter	<b>Application:</b>	Variety of electrical diagnostic and troubleshooting applications
<b>Special Features:</b>	Transfective Reverse-Contract Display; Lighted Dial; Built-in Lead Holder	<b>Material:</b>	ABS/Electronics
<b>Batteries:</b>	3 x AAA	<b>Auto-Power Off:</b>	Yes
<b>Jaw Size:</b>	1.4" (3.6 cm)	<b>Drop Protection:</b>	6.6' (2 m)
<b>Display:</b>	Transfective Reverse-Contrast with 6000 Count LCD	<b>Display Size:</b>	1.5" x 1.0" (3.83 x 2.6 cm)
<b>Functions:</b>	AC/DC Voltage, AC/DC Current, Resistance, Audible Continuity, Low Impedance, Non-Contact Voltage Testing, Diode Test, Capacitance, Frequency/Duty Cycle, Min/Max Value, Rel/Zero, Data Hold Capability	<b>Auto Ranging:</b>	Yes
<b>TRMS:</b>	Yes	<b>Voltage:</b>	1000V AC; 1000V DC
<b>Frequency:</b>	1Hz - 500 KHz	<b>Current:</b>	600A
<b>Capacitance:</b>	6000µF	<b>Ohms (Resistance):</b>	60M?
<b>AC Voltage:</b>	1000V	<b>DC Voltage:</b>	1000V
<b>DC Polarity Indicator:</b>	Yes	<b>DC Micro-Amp:</b>	No
<b>Temperature Range:</b>	-	<b>Ingress Protection:</b>	IP40
<b>Accuracy:</b>	See Instructions	<b>Standard:</b>	CAT IV 600V, CAT III 1000V, Class 2, Double Insulation, CE, UKCA
<b>Included:</b>	Clamp Meter; Right-Angle Input Test Leads; Storage Pouch; Instruction Manual; and 3 x AAA Batteries	<b>Overall Length:</b>	9.06" (2.30 cm)
<b>Overall Height:</b>	1.65" (4.2 cm)	<b>Overall Width:</b>	3.47" (8.8 cm)
<b>Weight:</b>	13 oz (369 g) Including Batteries		